

verykool I277 mobile phone

User Manual

The content of this manual is correct at the time of issuance. However, Verykool USA Inc. reserves the right to amend technology specifications without any prior notification.

Some descriptions in this manual may be different from the actual mobile phone, depending on differences in software and network suppliers.

Contents

1 Basics

1.1 Introduction

Thank you for choosing the **I277** GSM/GPRS digital mobile phone. After reading this guide you will be able to fully master the use of your **I277** mobile phone and appreciate all its functions and ease of use.

The **I277** mobile phone is designed for use on the GSM/GPRS networks. Not only the **I277** provides you with basic calling functions, but also with many practical functions such as a name card style phonebook, personalized 64 chord ring tones and pictures, clock, alarm, camera, video player, video recorder, audio player, T-Flash card support, sound recorder, calculator, calendar, GPRS surfing, MMS, and H-Free etc, to improve the time you spend on working and playing. Moreover, the **I277** uses a personalized user- interface and the perfect functional design to satisfy all your needs. The **I277** mobile phone is compatible with GSM/GPRS technology and has been approved by certification authorities both domestically and abroad.

All rights reserved.

1.2 Safety Notice

- If your mobile phone is lost or stolen, please contact the telecommunications authorities or a sales agent immediately to have a hold put on the SIM card. This will prevent economic loss caused by unauthorized calls made from your mobile phone.
- When you contact the telecommunications authorities or a sales agent, they will need to know the IMEI number of your mobile phone (remove battery to expose number located on the label on back of phone). Please copy this number and keep in a safe place for future use.
- In order to avoid the misuse of your mobile phone please take the following preventative measures:
 - Set the PIN number of your mobile phone's SIM card and change this number immediately if it becomes known to a third party.
 - Please keep the phone out of sight when leaving it in a vehicle. It is best to keep the phone on your person, or locked in the trunk.
 - Set call restrictions.

1.3 For Your Safety

Please read these safety guidelines before using your mobile phone to assure the safe and proper use of the phone.

1.3.1 General matters

- Please turn off your mobile phone on an airplane, hospital or any locations that may restrict mobile phone use. Otherwise, normal operation of electrical equipment and medical instruments will be affected. Please obey local regulations when using your mobile phone.
- While driving please obey local laws and regulations regarding mobile phone use. When using your phone while driving, please obey the following rules: Concentrate on driving and be aware of traffic conditions; Use your mobile phone hands-free function, . under poor driving conditions, please stop the car before -using your phone.
- Please obey laws, regulations and signs when near an area storing fuel, chemicals, or volatile materials.
- Please keep mobile phones, batteries and chargers out of reach of children.
- To prevent damage to your mobile phone, do not use other types of batteries or chargers; it could cause battery leakage, overheating, cracking, fire or other dangers.
- Please do not use your mobile phone near low signal or precision electronic equipment. Radio wave interference may cause the malfunctioning of such electronic equipment and other problems. Special attention must be paid near the following equipment: hearing aids, pacemakers and other electronic medical equipment, smoke detectors, automatic doors and other automatic control installations. To find out the effect of mobile phones on a pacemaker or other electronic medical equipment please contact the manufacturers or local sales agents of the equipment.
- This mobile phone has an auto" power on" function. Please refer to the mobile phone's clock setting to assure that the mobile phone will not automatically turn on during a plane flight.
- To avoid the mobile phone malfunctioning or catching fire, please do not violently impact, jolt or throw your mobile phone.
- Please do not place the battery, mobile phone or charger in a microwave oven or high-pressure equipment. Otherwise, it could lead to unexpected accidents such as damage to the circuitry or a fire.
- Please do not use your mobile phone near flammable or volatile gases, otherwise it may cause malfunctioning or fire.
- Please do not subject your mobile phone to high temperatures, high humidity or dusty places; otherwise it may lead to malfunction of your mobile phone.
- To avoid falling, malfunctioning or being damaged, please do not place your phone on uneven or unstable surfaces.

1.3.2 Phone Safety

- Do not disassemble or modify the mobile phone, as it will lead to damage such as battery leakage or circuitry failure.
- Please do not subject the LCD to impact or use the screen to strike things, as

this will damage the LCD board and cause leakage of the liquid crystal. There is a risk of blindness if the liquid crystal substance gets into the eyes. If this occurs, rinse eyes immediately with clear water (under no circumstances rub your eyes) and go immediately to a hospital for treatment.

- Under very rare circumstances using the mobile phone in certain model cars may negatively effect the internal electronic equipment. In order to assure your safety under such circumstances please do not use the mobile phone. If your car is equipped with an airbag, please do not place your phone on top of it or within the contact area of the airbag in order to avoid seriously harming the driver or passenger when the airbag inflates.
- Please do not use needles, pen tips, or other sharp objects on the keypad as this may damage the mobile phone or cause it to malfunction.
- Avoid letting the phone come into close contact with magnetic objects such as magnetic cards as the radiation waves of the mobile phone may erase the information stored on floppy disks, pay cards and credit cards.
- Please keep small metal objects, such as thumbtacks, far away from the receiver. When the receiver is in use it becomes magnetic and may attract these small metal objects and may cause injury or damage to the mobile phone.
- Do not expose the mobile phone to humidity, water or other liquids. If liquids enter the phone, it could cause short circuits, battery leaks or other malfunctions.
- Please use the mobile phone in a place away from landline telephones, televisions, radios, and automated office equipment to avoid affecting both the equipment and the mobile phone.

1.3.3 Battery Safety

- Do not disassemble or modify the battery, as this will cause the battery to leak, overheat, crack and catch fire.
- Do not dispose of old batteries with everyday domestic garbage. Please dispose of old batteries at the directed places with specific rules for their disposal.
- Please do not put/throw batteries into a fire, as this will cause the battery to catch fire and explode.
- When installing the battery, do not use force or pressure, as this will cause the battery to leak, overheat, crack and catch fire.
- Please do not use wires, needles or other metal objects to short-circuit the battery. Also, do not put the battery near necklaces or other metal objects, as this will cause the battery to leak, overheat, crack and catch fire.
- Please do not solder the contact points of the battery, as this will cause the battery to leak, overheat, crack and catch fire.
- If liquid from the battery goes into the eyes, there is a risk of blindness. If this occurs do not rub the eyes, but immediately rinse eyes with clear water and go to a hospital for treatment.
- Please do not use or place the battery near high temperatures such as near a

fire or heating vessel, as this will cause the battery to leak, overheat, crack and catch fire.

- If the battery overheats, changes color, or becomes distorted during use, charging, or storage, please stop using and replace it with a new battery.
- If the liquid from the battery touches skin or clothing, this may cause burning of the skin. Immediately use clear water to rinse and seek medical attention if necessary.
- If the battery leaks or gives off a strange odor, please remove the battery from the vicinity of the open fire to avoid a fire or explosion.
- Please do not let the battery become wet as this will cause the battery overheat, smoke and corrode.
- Please do not use or expose battery in high temperatures or direct sunlight, as this will cause the battery to leak and overheat, lower performance, and shorten the battery's life.
- Please do not continuously charge for more than 24 hours.
- Please place the battery in a cool, shady and well-ventilated place out of direct sunlight.
- The life of all mobile phone batteries is limited. The usable time of batteries decreases with frequent charging. When charging becomes ineffective this means that the battery is out of service and the battery should be replaced with a new one of the designated type.

1.3.4 Charger Safety

- Please do not disassemble or modify the charger, as it will lead to physical harm, electrical shock, fire or damage to the charger.
- Please use AC 110 to 220 volts. The use of any other voltage will cause battery leakage, fire and even damage to the mobile phone and charger.
- It is forbidden to short circuit the charger, as this will cause electrical shock, smoking and damage to the charger.
- Please do not use the charger if the power cord is damaged, as this will cause fire or electrical shock.
- Please immediately clean any dust gathered on the electrical outlet.
- Please do not place vessels with water near the charger in order to avoid water splashing onto the charger and causing an electrical shortage, leakage or other malfunction.
- If the charger comes in contact with water or other liquid the power must immediately be switched off to avoid an electrical short or shock, fire or malfunction of the charger.
- Please do not use the charger in bathroom or other excessive moist areas, as this will cause electrical shock, fire or damage to the charger.
- Please do not touch the charger with wet hands, as this will cause electrical shock.
- Do not modify or place heavy objects on the power cord, as this will cause electrical shock or fire.
- Before cleaning or maintenance please unplug the charger from the electrical

outlet.

- When unplugging charger, do not pull on the cord directly, hold on to the body of the charger to pull the charger out of outlet, as pulling on the cord will damage the cord and lead electrical shock or fire.
- Please do not charge in the following places: moist or humid places, dusty places or places with excessive vibration (this will cause malfunctioning); or near televisions, radios, electronic products (this will effect the picture and sound)

1.3.5 Cleaning and Maintenance

- The mobile phone, battery and charger are not water resistant. Please do not use them in restrooms or other excessively moist areas and likewise avoid allowing them to get wet in the rain.
- Use soft, dry cloth to clean the mobile phone, battery and charger.
- Please do not use alcohol, thinner, benzene or other solvents to wipe the mobile phone.

A dirty outlet will cause poor electrical contact, lose of power and even inability to recharge. Please clean regularly

2 Before Use

2.1 The Names and Explanation of Each Part

2.1.1 Appearance













2.1.2 Keypad Instructions

1. **OK key:** OK key function is the same as the left soft key.
2. **Menu key :** press this key for the main menu.

3. **Back key:** to perform the function of the prompt displayed in the lower right corner of the screen.
4. **Dial key:** to dial and pick up calls; on standby, to see all calls record list.
5. **Hang-up key:** to end a call or reject incoming calls, to return to the idle screen, long press to power on/off the handset.
6. **Camera key:** press the camera key to enter “Camera” menu.
7. **Side volume keys:** Press to adjust the volume when playing music, video, FM and TV.

Note: In this handbook, the phrase “press the key” refers to pressing and thereafter releasing a key; “Long press a key” refers to pressing a key and keeping it pressed for 2 seconds or longer.

2.1.3 Icon

Icon	Explanation	Location
	Signal intensity of network	At the top of screen
	Keyboard is locked	At the top of screen
	Vibration and sound	At the top of screen
	Ring	At the top of screen
	Vibration and silent	At the top of screen
	Earphone is inserted	At the top of screen
	Text message is received	At the top of screen
	Startup alarm	At the top of screen
	Shows the battery level	At the top of screen
	There are Missed calls	At the top of screen

2.2 Insertion of the SIM Card and Memory Card

Note: For Dual-SIM models, please select SIM1/SIM2 before proceeding to below steps

2.2.1 Insertion of SIM Card

The metal surface of the SIM card is very easily scraped. Before inserting into the phone you must carefully remove it.

- Turn off the phone; remove the battery and unplug other external power sources.
- Insert the SIM card into the SIM slot.
- When you need to remove the SIM card, please first turn off the phone, remove the battery, then remove the SIM card.

2.2.2 Insertion of Memory Card

- Turn off the phone; remove the battery and unplug other external power sources.
- Put the Memory Card into the Memory Card slot.
- When you need to remove the Memory Card, please first turn off the phone, remove the battery, then remove .

2.3 Battery

The battery is initially charged only 50% of its total capacity. Please fully recharge the battery after completely discharging for the first 3 times, to get the best of your battery performance

2.3.1 Removal and Installation of the Battery

- When removing the battery follow the below steps:
 - ① Push the battery cover towards the bottom;
 - ② Lift the bottom part of the battery, take out the battery from the mobile-phone.

Warning: You must turn off your mobile phone before removing the battery. Under no circumstances should you remove the battery when the mobile phone is on as this may damage the SIM card and your mobile phone.

- When installing the battery follow the below steps:
 - ① Following the direction of the arrow, push the battery to insert in to the mobile-phone.
 - ② Place the battery cover.
 - ③ Push the battery cover up.

2.3.2 Battery charging

- The charger connector with the bottom of the phone (with the arrow pointing upward).
- The battery capacity Icon will start flashing periodically; when charging at power-off status, charging indicator on the screen means the phone is charging now. If you are using a phone in low battery, it may need certain time for charging indicator to appear on the screen after starting to charge.
- When the Capacity Icon is full and doesn't flash any more, the charging process is complete. If your phone is charged in power off status, “charging complete” will also show. Charging process usually takes 1-2.5 hours. Battery, phone and charger normally heats up during the charging process.
- When the charging is complete, disconnect the phone and the charger from the AC power outlet.

Note: Be sure to charge in ventilated place with the temperature ranging from -10°C to +45°C, and **always use** the charger provided by the original manufacturer. Using unauthorized charger may cause damage, which is outside of the warranty coverage.

2.4 Safety password

PIN code/PUK code

The PIN code (individual identification number) prevents your SIM card from illegal use. The PIN code is generally provided with the SIM card. If the wrong PIN code is entered 3 consecutive times, it will be locked and the PUK code must be entered to unlock. Please consult with your network provider for more details. (PIN code default is 1234).

3 Features

3.1 Function hotkey

Function	Hotkey	Mode
----------	--------	------

Power on/off	Long press the Hang-up key	In any screen
Control receiver volume	Press Side volume keys	Calling screen
Enter the main menu	Press the Menu key	Idle screen
Silent/Normal mode	Long click the # key	Idle screen

Note: For Dual-SIM models, please select SIM1/SIM2 before proceeding to below steps.

3.2 Dialing

You may dial and receive calls on your phone when the symbol of your network provider appears on the screen. The information bar on the upper left corner of the screen indicates network strength (the signal is strongest when there are four lines visible).

3.3 Rejecting calls

You can press the **hang up key** to reject any incoming call.

3.4 Receiving calls

You can choose different modes to receive calls. If the earphones are already plugged in, you can use the button located on the earphones to answer the call. If it is inconvenient to press the button, then you can set the “**Auto**” as “**On**”, with the earphones plugged in, and the phone will automatically pick up after ringing or vibrating for 5 seconds. If you have set the “**Any Key**”, you can pick up the call by pressing any key other than the **hang up key**.

3.5 Ending a call

During a call you can press the **hang up key** to end a call. You can also cancel a call you have just dialled by pressing the **hang up key**.

3.6 Emergency calls

If you are located within the network area (you can find this out by referring to the network strength indicator located on the upper left-hand corner of your mobile phone screen), you should be able to make emergency calls. If your network provider does not provide roaming at your current location, “**Emergency**” will appear on the screen. If you are located within a network area, even if you do not have a SIM card, you will be able to transmit emergency calls.

3.7 Extension dialing

Some fixed phone extensions cannot be called directly. You need to input a “**P**” before the extension number. The “**P**” can be input at the dial screen by long clicking the *** key** and switch to it.

3.8 Call history

Get in this menu to view the missed/received/dialed calls.

3.9 Call divert

After activating this function, the network will notify you that you have a new incoming call when you are talking on the phone. For details of how to use this function you can contact your network operator.

3.10 Call waiting

The call diversion network service permits you to divert, under certain preset situations, certain incoming calls to a telephone number designated by you. This

service requires network support. Please contact your network provider to activate this service. You can set and cancel the incoming call diversion function of your mobile phone.

3.11 Call barring

The **Call Barring** allows the user to prevent incoming or outgoing calls based on user-defined conditions. The network provider provides you with a 4 digit **Barring PW** to allow you to activate the “**Call Barring**” service. When you use this function, please contact your network provider

3.12 Turning the Phone On and Off

To turn on or off the phone please long press the Hang-up key.

4 Function Menu

4.1 How to Use the Function Menu

4.1.1 Scroll to select Function

- On standby, press the **ok key** -to enter the main function menu. During a call click “**Options**” to enter the call option menu, then use Touch-screen slide to scroll to the desired item on the menu and press the **ok key** to select the function.

- In all the menu and submenu, use Touch-screen slide to scroll to the desired function and press the **left soft key** to enter the function item.

4.1.2 Shortcut select function

Most main menus and submenus have speed numbers. This speed number is the function’s corresponding index number.

- On standby, press the **OK key** to enter the main menu, Touch-screen slide to scroll to the desired item on the menu.

- Enter the main menu’s speed number to enter the corresponding option. Enter the submenu’s speed number to select the corresponding option.

4.1.3 Exit Menu

Usually, you can exit the current menu by click the “**Back**”. You can also press the **hang-up key** to return to the idle screen.

4.2 File manager

Click “**Ok**” to enter this submenu, menu display “**Phone**” and “**Memory Card**” (if the Memory card has been inserted into the mobile-phone).

- **Open** to display all the files and folders in the root.
- **New Folder** to create a new folder.
- **Format** to format the **Phone** or **Memory Card**, it will delete all of the data and file.
- **Rename** to rename your **Phone** or **Memory Card**.
- **Details** to show the Name/Total size/Free size of your **Phone** or **Memory Card**.

Open the root, it will display the file or folder list, select a folder and press the left soft key “**Options**”:

- **Open** to display the content in the current folder.
- **New Folder** to create a new folder.
- **Rename** to change the current file or folder name.

- **Delete** to delete the current file or folder.
- **Sort by** to select sort the folders **By Name**, **By Type**, **By Time** and **By Size**, or not array to select **None**.

Select one file and press the left soft key “**Options**”. It may show different items according to the different file format:

- **View** to view the image file.
- **Play** to play multimedia file.
- **Use** to use the different file in different usage. The music file can be used in **User Profile** as ringtone. The image file can be used in **Power On/Off Display**, **Wallpaper** and **Screen Saver**.
- **Send** to send the file by **MMS**.
- **Detail** to display detail information about **Date** and **Size**.
- **Rename** to change the file name.
- **Copy** to copy the current file to other place. Press **OK** to start, press **Select** to copy the file in current position, press **Open** to enter the folder, press **New Folder** to set up a new folder.
- **Move** to move the current file to other place, same as **Copy**.
- **Delete** to delete the current file (**Note**: if the file attribute is **Read Only**, it can not be deleted.).
- **Delete all files** to delete all files in the current folder.
- **Mark several** to multi-select several files to copy/delete/move.
- **Sort** to sort the files **By Name**, **By Type**, **By Time** and **By Size**, or **None**.

4.3 Phonebook

Note: For Dual-SIM models, please select SIM1/SIM2 before proceeding to below steps

You can use the phonebook function “To Phone” to save name card information such as **Name**, **Number**, **Caller ringtone** and **Caller Group**.

Note: This phone is able to save up to 500 phone book records, and the record storage of SIM card is decided by the capacity of the SIM card.

The options of this result by the **ok** key are following:

- **View** : view the details of entry
- **Send text message** : to send text message to the current phone entry
- **Send multimedia message** : to send the multimedia message to the current entry.
- **Call** : to make a call directly.
- **IP dial** : activate the IP dial-up of numbers in the phonebook.
- **Edit** : edit the entry.
- **Delete** : delete the entry.
- **Copy** : copy the entry.
- **Move** : move the entry.
- **Send contact** : send the entry of “as text message”.”as multimedia message” and “via Bluetooth”.
- **Add to blacklist** : add the entry to blacklist.
- **Caller groups** : he phone is programmed with 5 caller groups. You can make

some individual settings for each group, such as rename, ring type, incoming call picture and each group member's personal setting.

- **Phonebook settings:** set the phonebook in nine categories: Preferred storage, Speed dial, My number, vCard version, Extra numbers, Memory status, Copy contacts, Move contacts and Delete all contacts.

4.4 Fun & Games

4.4.1 Java

Show the JAVA applications list installed. You can install the Java programs through file manage. At this list, you can launch or delete them by option menus

4.4.2 Java settings

JAVA settings include JAVA audio, JAVA backlight, Network setting, etc.

4.4.3 Java default security

In this menu you can set Third party、Untrusted domain、Restore settings and domain options

4.4.4 Java network

In this menu you can set network for java.

4.4.5 Games

In this menu there is a puzzle game for your leisure time entertainment.

4.5 Call center

Note: For Dual-SIM models, please select SIM1/SIM2 before proceeding to below steps

4.5.1 Call history

In this menu you can view all call records, including missed calls, received calls, dialed calls; click on the above have been received, missed, dialed the phone icon, enter the corresponding call log list. In the call log list, select records, click on the options for the following operations:

- **View:** to view the current record.
- **Call:** to call the current record.
- **Save to phonebook:** to save the current number to phonebook.
- **Add to blacklist:** to add the current record to blacklist.
- **Edit before call:** to edit the current record before call.
- **Delete:** to delete the current record.
- **Delete all:** to delete all call log records.
- **Advanced:** to set **call timers, call cost, text msg.counter** and **GPRS counter**.

4.5.2 Call settings

In this menu you can set **Caller ID, Call waiting, Call divert, Call barring, Line switching, Closed user group** and **Advance settings**.

In the **Advance settings** you can set **Blacklist, Auto redial, IP dial, Call time display, Call time reminder, Auto quick end, Reject by SMS** and **Emergency & Service call**.

4.6 Messaging

This feature allows you to send, receive, store and edit all kinds of information, and its network must support a variety of features, please contact the company with the network operator.

Note: For Dual-SIM models, please select SIM1/SIM2 before proceeding to below steps

4.6.1 Write message

Text message

Before writing a text message, please confirm that you have set the short message service centre number.

You can edit your short message by entering the **Text Message** submenu.

Click the **option** to enter the **Option** menu:

- **Send to** : click ok key to enter number, insert the number then click the ok key can select **“send”**, **“edit recipient”**, **“remove recipient”** and **“remove all recipients”**.
- **Input Method**: to offer 8 kinds of input methods.
- **Insert template**: to insert character information of prearranging at the currently cursor place.
- **Advanced** : in this menu you can set **“insert object”**, **“insert number”**, **“insert name”**, **“insert bookmark”** and **“text format”**.
- **Save to Drafts**: save this message to Drafts.

Multimedia message

When you select **“Multimedia message”**, click the **“ok”** to write message interface, you can input content. After finishing it, click the **“Options”**, have options as follows:

- **Send to** Complete editing of the current MMS.
- **Input Method** to choose one kind as acquiescence characters editor.
- **Text options**
- **Add picture** to select a picture from **[File Manager]** submenu or take picture and insert into the current page.
- **Add sound** to select an audio from **[File Manager]** submenu or record sound and insert into the current page.
- **Add Video** to select a video from **[File Manager]** submenu or record video and insert into the current page.
- **Add subject to** edit the subject for this message.
- **Preview MMS** to preview the current MMS.
- **Slide options** in this menu you can set **“add slide behind”**, **“add slide before”** or **“slide timing”**.
- **Advanced** in this menu you can select **“insert text template”**, **“insert attachment”**, **“insert contact number”**, **“insert contact name”** or **“insert bookmark”**.
- **Save to Drafts** to save the message to Drafts.
- **Save as template** to save as template
- **Details** in this menu you can

Note: Some of the options above only appear under certain circumstances, for example, "Delete Slide" only appears when the current MMS exceeds one page. Each page of a MMS can only contain one picture and one sound. When the current page contains a sound or picture, "Edit image" or "Edit Audio" will appear. When editing an MMS, the status information line bar at the top of the

screen will display the following: the current page/total pages; and the entire size of the MMS.

4.6.2 Inbox

Text message

Enter the “**Inbox**” submenu to view received messages. When you receive a short message, your mobile phone will vibrate (if **Alert Type** set to the **Vibration**) and ring (if **Alert Type** set to the **Ring**), display the prompt information. If you do not wish to read it immediately, after you exit this interface, the envelope icon appears at the top of the screen on standby and the short message will automatically be saved on the SIM card. The amount of short messages that can be saved (this includes received messages as well as saved messages) is based on the memory size of the SIM card.

- When viewing the short message list in “**Inbox**”, the sender’s phone number or name (if the name has already been saved in the phonebook) will be displayed, and show that receives the date of short messages by floating item.
- When looking at the short message list, you can use the Touch-screen slide to select the short message. When the “**Inbox**” short message list appears, you can click the “**Ok**” to read the detailed contents of a message, the date and time of receipt and the name (if the name has already been saved in the phonebook) or telephone number of the sender. At this time you can also click the “**Option**” to perform the following operations:
 - View** view the message.
 - Reply by SMS** to send the text message to the sender of the current message.
 - Reply by MMS** to send the multimedia message to the sender of the current message.
 - Call sender** to call the sender of the current message.
 - Forward** to edit the current message Send.
 - Delete** to delete the current short message
 - Delete all** to delete all message of the inbox.
 - Save to phonebook** save the sender to the phonebook.

In view the message interface you can also click the “**Options**” to perform the following operations:

- Reply** to send a short message to the sender of the current message.
- Call sender** to call the sender of the current message.
- Forward** to edit the current message Send.
- Delete** to delete the current short message.
- Advanced** to use number, URL and USSD

Multimedia message

Enter the “**Inbox**” submenu. Your mobile phone will display a list of the MMS in the “**Inbox**” (include download prompt). Use the Touch-screen slide to scroll to the MMS, you wish to read, by clicking the “**Options**”, you can carry out the following operations on the current MMS.

- **Download:** to download the current MMS content (if the MMS is not download to the phone).
- **View:** to look over the current MMS content.
- **Reply:** to edit the MMS to reply sender, at the same time, subject change to "Re:" and old subject.
- **Reply by SMS:** to edit the SMS to reply sender
- **Reply all:** to edit the MMS to reply all, at the same time, subject change to "Re:" and old subject.
- **Forward:** to edit the correlative message to forward the current MMS, at the same time, subject change to "Fw:" and old subject.
- **Delete:** to delete the current MMS.
- **Delete All:** to delete all the MMS in the inbox.
- **Properties:** to can look over the sender's number, subject, and sent time and date, MMS Size and so on.
- **Use Details:** to pick up the number of sender and the bookmarks of content. You can Dial the number or Save to Phone Book, also you can Goto the bookmarks or add bookmarks.

4.6.3 Drafts

Text message

In the Outbox list interface, select a message, Click the “option”, you can make the following operation.

- **View** to view the current message
- **Send** to send the current message
- **Edit** to edit the current message.
- **Delete** to delete the current message.
- **Delete all** to delete all message in “Drafts”

Multimedia message

Boxes in the Outbox list interface, select an MMS, Click the “option, you can make the following operation.

- **Send:** Send the article MMS.
- **Play:** Play the article MMS.
- **Editor:** enter the MMS editing interface, you can edit the MMS.
- **Delete:** Delete the clause MMS.
- **Delete all:** Delete the mailbox has not made all of the information.

4.6.4 Outbox

E Enter the “**Outbox**” submenu to view the short messages (saved in the SIM card and owner phone) in the mobile phone. After the “**Outbox**” short message list appears, you can use the Touch-screen to scroll and select the short message; click the “**Ok**” to read the detailed contents of the selected short messages. At this time you may also click “**Options**” to perform the following functions:

- **View** to view the current message
- **Resend** to send the current message.
- **Edit** to edit the current message.

- **Delete** to delete the current short message.
- **Delete All** to delete all the messages in “Outbox”

4.6.5 Sent messages

This mailbox store has send a message

4.6.6 Delete messages

Can be removed separately from Inbox, Outbox, Sent messages, drafts or all of the information to delete all.

4.6.7 Broadcast message

In this menu you can use the broadcast message.

4.6.8 Templates

Text message

Click the “ok” to enter information template list, can **edit** or **remove** the template message or **Write Message**.

Multimedia message

Click the "Ok" to enter information template list, can View it, Properties and Write Message

4.6.9 Message settings

Text message

When using the short message function you must first make the necessary settings.

Enter the “**Message Settings**” submenu to select the following operations:

- **Profile Setting** Please contact your network provider to get the **SC Address**. Profile list have one profile, two profiles and four profiles because the different network supports and SIM card. Select one **Profile**, press the **left soft key “Edit”**, can set the **Profile Name**, **SC Address**, **Valid Period** and **Message Type**. During **Valid Period**, the short message service centre will continuously resend a message until it is received. The message **Valid Period** is applicable for all sent messages. You can set the message **Valid Period** as any of the following: “**1 hour**”, “**6 hours**”, “**12 hours**”, “**1 day**”, “**3 days**”, “**1 Week**” or “**maximum**”. The network operators must support this function for it to be available. **Message Type** can select the **Text**, **Fax**, **Page**, **E-mail** by the **left/right keys**.

Note: Message Validity Perid, Fax, Page and E-mail need support by the network operator.

- **Common Setting** to set **On/Off** for the **Delivery Report**. If you set it as “**On**”, when the recipient receives your short message, or if the short message is not received for some reason, the short message center will send a status report so that you can see whether the message has been delivered.

Note: The network operator must support this function for it to be available.

- **Memory Status** to display the memory by **n/m** form in the SIM card and

phone, thereinto, “n” denotes the current memory message, “m” denotes the most message capability in the SIM card or phone. Your mobile-phone can save 200 items (include Inbox and Outbox) SMS at most. SMS numbers are decided with SIM card capability in the SIM card.

- **Preferred Storage** to select to save the messages to “SIM” or “Phone”.

Multimedia message

The user must make the necessary settings in order to use the multimedia message.

Enter the "MMS Settings" submenu and make the following settings:

Profiles

You can Activate profile and View profile.

Common settings

Enter the “common setting” submenu and make the following settings:

- **Compose:** include **Creation Mode, Image Resizing** and **Auto Signature**.
- **Sending:** include **Validity period, Delivery report, Read report, Priority, Slide Timing, Delivery time**.
- **Retrieval:** include **Home network, Roaming, Read Report, and Delivery Report**.

- **Memory Status:** view Usage, Used Space, and Free Space.

4.7 Multimedia

4.7.1 Mobile TV

I In this menu you can enjoy watching mobile TV

4.7.2 Camera

Camera Settings

I In the preview mode of the camera click “Options”, to access the following:

- **Photos:** to enter photos folder, view the pictures saved.
- **Camera settings:** Click to select to set **Shutter sounds, EV, Contrast, Anti-flicker , Delay timer** and **Cont. shot**, if you click the “Ok”, the settings will be activate.
- **Image settings:** to set the **Image size** and **Image quality**. **Image size** can be selected from **240×400、80×60、160×120、320×240、640x480**; **Image quality** can be selected from **Normal, Good** and **Low**.
- **White balance:** you can select from **Auto, Daylight, Tungsten, Fluorescent, Cloud, and Incandescence**.
- **Scene mode:** you can choose **Auto** or **Night**, you only choose **Night** in dark environment.
- **Effect Settings:** to set the special effect from **Normal, Grayscale, Sepia, Sepia green, Sepia blue** and **Color invert** when you are taking photo.
- **Sensor Select:** to select camera 1 or camera 2.
- **Storage:** to set the storage of the photos from **Phone** or **Memory card**.
- **Restore Default:** to restore the settings of camera to default setting

except the self capture mode.

Taking a photo

- After framing the picture you wish to take, keep the camera steady and press the **Camera key** to take pictures. You can view the photos in the “**Image Viewer**” menu, or in **File Manager**.

4.7.3 Image viewer

Select the “**Image Viewer**” menu; you can conveniently view the photos listed. Click the “**Options**” to select the following contents: **View, Browse Style, Use, Send, Rename, Delete, Delete All Files, Sort by and Storage**.

- **View**: to view the photo.
- **Browse mode**: to choose view mode (matrix mode/list mode).
- **Use**: to set the photo as **Wallpaper, Screen Saver or Caller picture**.
- **Send**: to send the photo by **MMS**, but it will depend on the MMS space size, screen size, and so on.
- **Rename**: to change the name of the selected photo.
- **Delete**: to delete the selected photo.
- **Delete all files**: Delete all saved pictures
- **Sort By**: to sort the photo as following rank(by name/by type/by time/by size)
- **Storage**: to choose the viewer path.

4.7.4 Video recorder

To enter the “**Video Recorder**” menu, the recorder displays the preview window.

Video Recorder Settings

Click the “**Options**” for the following operations: :

- **Camcorder Settings**: to set content as follows, include **EV, Night Mode** and **Anti-flicker**. Click the “**Ok**” to activate the current settings.
- **Video Setting**: to set the **Video Quality, Size limit reached, Time limit reached** and **Record audio**.
- **White balance**: you can select from **Auto, Daylight, Tungsten, Fluorescent, Cloud, and Incandescence**.
- **Effect Setting**: to set the special effect for the movie.
- **Storage**: to set the storage of the video from **Phone or Memory card**.
- **Restore Default**: to restore the default settings of video.

Video

- In the preview screen, click the “**ok**” to begin to kinescope.
- Click “**ok**” to pause recording, then click “**ok**” again to continue recording.
- When a video is recording, touch “**Stop**”, stop and save the video, then return to the preview mode.

You can view the videos from the “**Video Player**” menu or in file manager

4.7.5 Media player

In this menu you can play video and music. Must be added the list of files to play videos and music, the specific steps: In the Media player menu, select My playlists, select the options "new" to create a new file, into the file and select the options "add" to add video files or music files from T Card , add after the success that can play

video and music.

4.7.6 Sound recorder

In this menu, mobile-phone can record sound. The format will be **AMR**, **WAV** or **AWB**. Click the start button to start recording. When recording, click the pause button to select “**Pause**” or “**Cont.**”, can pause or continue recording, Click the Stop button to select “**Stop**”, you can also edit and save the file. The recorded file is saved in [Audio] folder.

Select “**Options**” and access the following options:

- **New record**: to record a new sound.
- **Play**: to play the current record.
- **Append**: for **AMR** and **AWB** format, you can append the record to the current file, and save it as the same file.
- **Rename**: to change the name of the sound file.
- **Delete**: to delete the sound file.
- **Delete all files**: to delete all sound files.
- **Settings**: to change the file format. You can select **AMR**, **WAV** or **AWB** by the **left/right key**.
- **Use**: to set the current recorded file as the ringtone in the **User Profile**.
- **Send**: to send the current recorded file by **MMS**.

4.7.7 FM radio

Enter this menu, press **Adjusting the volume keys** to adjust the volume, Click the icon for stickers to adjust the channel, click the “ok” to control the Fm radio to play. Click the “**option**” can select the operation as follows:

- **Channel list** You can set up to 20 FM channels.
- **Manual input** You can input the frequency of FM radio.
- **Preset auto search** The auto search will acquire available FM radio frequencies and establish the channel list.
- **Settings** to set the Record format, Audio quality and Record storage.
- **Record** Records the radio broadcast.
- **Append** Regarding the **AMR** document, may supplement the sound recording in the current recording document, and will possess in finally the sound recording record retention current document.
- **File list** display the recorded files.

4.8 Organizer

4.8.1 Calendar

Click the “**Options**”:

- **View today** view the pre-saved event of today.
- **View all** view all the pre-saved events.
- **Add event** add an event as **Reminder**, **Meeting** or **Course**.
- **Jump to date** jump to a specified date of your preference
- **Go to weekly/monthly view** switch the format of the calendar between weekly view and monthly view.

4.8.2 Tasks

Display all the task arrangement. If there is no task, it will show Empty, click

“**Add**” to create a task. Otherwise, click “**Options**” to enter the option menu:

- **View** view and edit the current task.
- **Add** add a new task. You can choose the task type from **Date**, **Call** and **Anniversary**.
- **Edit** edit the current task.
- **Delete** delete the current task.
- **Delete all** delete all tasks.
- **Send vCalendar** send the task by **SMS** or **MMS**.
- **Save as file** save the task as a file.

4.8.3 Alarm

The mobile-phone can set up to five alarms, Selecting one alarm, you can turn on/off, set the time, repeat mode, snooze time, and alert type.

4.8.4 World clock

Enter the World Clock submenu, display world time zone map, move coordinate location by the **left/right keys**, the interface will show the city time located by the coordinates

4.8.5 Notes

In this menu you can create and edit notes.

4.9 Settings

4.9.1 Pen calibration

For calibration of the screen, touch the center of the cross on the screen.

4.9.2 Phone settings

In this menu you can set **Time and date**, **Schedule power on/off**, **Language**, **Pref. input methods**, **Encoding**, **Display**, **Auto update of date and time**, **UART settings** and **Misc. settings**.

4.9.3 Network settings

In this menu you can set the network **Network selection** and **Preferences**.

4.9.4 Security settings

In this menu you can set **SIM Security settings**, **Phone lock**, **Auto keypad lock** and **Change password**.

4.9.5 Restore factory settings

Enter the “**Restore Factory Settings**” submenu. Here you can restore the relevant settings to the manufacturer’s default settings.

Note: Restoring Factory settings requires the correct handset unlock code to be entered. Some settings cannot be restored to the manufacturer’s settings until the phone is rebooted.

4.9.6 Sound effects

Set the audio effect of audio player: Equalizer effect.

4.10 User profiles

Your mobile phone provides five different user profiles that you can select, for different occasions.

- **General** for use under general circumstances.
- **Meeting** for use in meetings. This requires presetting (for example, Alert Type is set to Vibration only).

- **Outdoor** for use in outdoor activities. This requires presetting (for example, you can set raise the volume of the receiver and ring tone).
- **Indoor** for use in indoor activities. This requires presetting.
- **Headset** for use in headset activities, this mode will activate when the earphone is inserted. This requires presetting (for example, you can lower the volume of the receiver and ring tone).
- **Bluetooth** for use in Bluetooth activities, this mode will activate when connecting to a Bluetooth device.

Note: These five profiles have already been set and the default profile is “General” when the mobile phone leaves the factory. On standby, you can long press the # key to turn silence on or off.

Press the **up/down** keys to select a profile, then click the “Options”:

Activate: to activate selecting profile.

Customize: for you to customize the profile.

Select “Customize” menu, it will display the menu as follows:

- **Tone Setup:** customize different ring tones with different option, for example, incoming call, power on or off, and so on.
- **Volume:** Two type of volume can be set: **Ring Tone** (including incoming call, alarm, power on, power off, message tone) and **Key Tone** (associated with key press).
- **Alert Type:** set the kind of alert for incoming calls. You can select from four types: **Ring Only/Vibration Only/Vibration and Ring/Vibration then Ring.**
- **Ring Type:** set the mode of ring, including **Single, Repeat and Ascending.**
- **Extra Tone:** The user can turn on or off the tone as follows: **Warning, Error, Camp on and Connect.**
- **Answer Mode :** The user can select different modes for answering: Any Key (except for the Hang-up key, right soft key) and Auto (when the earphone is inserted)

4.11 Extra

4.11.1 Calculator

Click the buttons on the screen to calculate.

4.11.2 Unit Converter

Select from the unit options to convert.

4.11.3 Currency converter

Select the currency to convert.

4.11.4 Stopwatch

In this menu you can use the **Typical stopwatch** and **nWay stopwatch.**

4.12 Services

4.12.1 STK*

Press the **up/down** keys to select “STK”. Press the left soft key to enter the “STK” main menu. Here you can use the value-added services provided by your network operator.

Your mobile phone supports STK functions. But if your SIM card and network operator does not provide this service, then you will not be able to use this function. For more information please contact your network operator

4.12.2 Internet service

Your mobile phone supports wireless application protocol (Internet service) service. You can access many different WAP services such as news, weather reports, flight information, and others. These services are customized for mobile phones and maintained by WAP service providers.

Network support is necessary for Internet services. Please contact your network provider and/or the service provider of the desired service. The service provider will also provide instructions on how to use their service.

In the services menu, use the Touch-screen to scroll and select “**Internet service**” and click “ok” to enter the menu. Here you will see the following menu options: “**Homepage**”, “**Bookmarks**”, “**Recent Pages**”, “**Input address**”, “**Service Inbox**” and “**Settings**”.

Homepage

Select “**Homepage**” to enter the home page, use this menu to connect your phone to the network and load the home page of the service provider. The Home page is the WAP site set upon activation . Home page is set in the [**Settings**]\[**Edit Profile**]\[**Homepage**].

Bookmarks

Display the bookmark list. Use the Touch-screen to scroll and select a bookmark, click “**Options**” to access the following options:

Go to: connect to the address appointed.

Edit: edit the **Title** and **Address** of the bookmark.

Send: send the bookmark to others via SMS or MMS.

Delete: delete the selected bookmark.

Delete All: delete all bookmarks.

Add Bookmark: edit the name and address of a new bookmark.

Note: If the bookmark is empty, you need to input the address first, then connect..

Recent Pages

Shows the list of webpages recently visited.

Input address

Use this menu to manually enter the URL address of a website and access the website. Except for **Bookmarks** and **Recent Pages**, **Enter Address** provides the other route to access the website.

Service Inbox

Select “**Service Inbox**” to view received service messages.

The mobile phone can receive service messages sent by your service provider. For example, service messages may consist of notifications on news briefings, or a line of a text message, or a WAP service address.

Settings

Select “**Settings**” to enter settings for online browsing, including”**Select SIM**”, “**Profiles**”, “**Browser Options**”, “**Service Message Settings**”, “**Clear Cache**”and

“Clear Cookies”

- **Select SIM** to select use sim1 or sim 2 (For Dual-SIM models only).
- **Profiles** to display the edit profile list. After edit and save the list, select “**Activate account**” to activate.
 - **Account name:** change the name.
 - **Homepage:** change the homepage.
 - **Data Account:** select the data account from GSM Data and GPRS.
 - **Connection Type:** select the connection type from **WAP** and **HTTP**, depend on the gateway. Press the **up\down** keys to select.

If you select **WAP**, you can set:

- **IP Address:** input the gateway **IP address**.
- **Security:** set joint security, depend on the gateway.
 - If you select **HTTP**, you can set:
 - **Proxy Address:** input gateway **Proxy address**.
Proxy Port: set the proxy port.
 - **Username:** set the user ID for APN Service.
 - **Password:** set the user password for APN Service.
- **Browser Options** set the **Timeout** and **Show Images**:
 - **Timeout:** set a time limit, integer of 30-300 (second) , if there is no data entered or transferred beyond this time limit the service will automatically turn off.
 - **Show Images:** to set the images, show and not show, by turning **On** or **Off**.
 - **Cache:** turn on/off cache.
 - **Cookies:** turn on/off cookies.
- **Service Message Settings** set to incept or not incept the WAP service message.
- **Clear Cache** Clear the cache memory of the data or services that you have visited
- **Clear Cookies** Clear the cookies of the data or services that you have visited

Note: If you tried to visit, or successfully visited confidential information that required a password (such as a bank account), please clear your mobile phone’s cache memory each time for your protection.

4.13 Connectivity

4.13.1 Bluetooth

In this menu, you can access the following operations:

- **Power** Click to select Bluetooth **on/off**.
- **Visibility** Click to select **Bluetooth visibility on/off**.
- **My device** Select an item, press the left key “option” and select the following operations:
 - **Connect** connect to a device shown on the searched list.

- **Disconnect** Disconnect from the device.
- **Rename** Edit the name of the device.
- **Delete** Delete this record.
- **Delete All** Delete all records.
- **Service list** Demonstrates this equipment's record of service.
- **Inquiry new Device** Searches for new Bluetooth devices within range.
- **Search audio device** searches for Bluetooth devices which has connected with this handset before and new devices within range.
- **My name** You can edit the Bluetooth name in this menu.
- **Advanced** press left soft key “ok ” then select the operation as follows:
 - **Audio path:** Set Leave in phone or Forward to BT headset.
 - **Storage :** select your storage to **phone, memory card** or **Always ask.**
 - **Sharing permission:** choose **fully control** or **Read only.**
 - **My address:** display my address.

4.13.2 Data account

GPRS

In this menu, the mobile-phone will show the **Data Account** list of GPRS data. You can select and edit the GPRS data:

- Account Name:** edit specify a name for the account
- APN:** edit APN.
- User Name:** edit the user identification to login the APN.
- Password:** edit the password to login the APN.
- Auth. Type:** set the authority type to Normal or Secure.
- Primary DNS:** edit the Primary DNS address.
- Secondary DNS:** to edit the Secondary DNS address.

5 Input Method

5.1 General Outline

This mobile phone provides many input methods. Character entry functions permitted by this mobile phone are:

- Inputting and editing of short messages
- Inputting and editing of names in the phone book
- Looking up the phone entry by name
- Editing of text in MMS.

6. Declaration of Conformity

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this

equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

THIS MOBILE PHONE MEETS THE INTERNATIONAL RECOMMENDATIONS FOR EXPOSURE TO RADIO WAVES

Your mobile phone is a radio transmitter and receiver. It is designed and manufactured not to exceed the limits for exposure to radio frequency (RF) energy defined by the international standards. These recommendations have been established by the International Commission on Non-Ionizing Radiation Protection (ICNIRP) and, the Institute of Electrical and Electronics Engineers (IEEE) that forecast a substantial safety margin for assuring the protection of all persons, regardless of age and health. The exposure recommendations for mobile phones use a measurement unit known as the Specific Absorption Rate (SAR). The SAR limit recommended by the ICNIRP for the mobile phones used by the general public is 2.0W/kg averaged over ten grams of tissue and, is 1,6W/kg averaged over one gram of tissue by IEEE Std 1528 for the head.

Tests for SAR have been conducted using recommended operating positions with the mobile phone transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR levels of the mobile phone while operating are generally below the maximum SAR value. This is because the phone is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a base station antenna, the lower the power output.

While there may be differences between the SAR levels of various phones and at various positions, they all meet the international protection standards for exposure to

radio waves.

The highest SAR value for this model phone when tested was 0.62W/kg at ear and 0.39 W/kg for use close to the body.

For limiting the radio waves exposure, it is recommended to reduce the mobile phone call duration or to use a headset. The purpose of those precautions is to take the mobile phone away from the head and the body.

For body worn operation, this phone has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of 1.5cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

7. Hearing Aid Compatibility

Mobile Phone i277 has been tested and received an HAC rating of M3/T3. The Phone has been tested and classified as eligible for its use with earphones for some of the device's features. Nevertheless, it is possible that this telephone may utilize a newer mobile technology not yet been tested for its use with earphones. It is important that you test the different telephone features exhaustively, in different places, utilizing its earphone to determine if you experience some background noise of interference. Consult with your local customer service center to get information about the refund and changes policy, and to obtain information about the compatibility with earphones