



www.alcatelonetouch.com

For more information on how to use the phone, please go to www.alcatelonetouch.com and download the complete user manual. Moreover, on the website, you can also find answers to frequently asked questions, upgrade the software via ONE TOUCH Upgrade, and so much more.

ALCATELOnetouch.

It's all about you

ALCATELOnetouch.

Note:

This is a shared user manual for ONE TOUCH 4010X/ONE TOUCH 4010D.

Table of Contents

Sa	fety	and use	4
G	ener	al information	11
1	You	ır mobile	14
	1.1	Keys and connectors	
	1.2	Getting started	
	1.3	Home screen	20
2	Tex	t input	
	2.1	Using Onscreen Keyboard	
	2.2	Text editing	
3	Pho	one call, Call log and Contacts	31
	3.1	Phone	
	3.2	Call log	
	3.3	Contacts	
4	Go	ogle Messaging, Gmail/Email, Google Talk	45
	4.1	Google Messaging	45
	4.2	Gmail/Email	51
	4.3	Google Talk	56
5	Go	ogle Calendar & Clock & Calculator &	
	Nev	ws & Weather	60
	5.1	Google Calendar	60
	5.2	Clock	62
	5.3	Calculator	63
	5.4	News & Weather	65
6	Get	tting connected	67
	6. I	Connecting to the Internet	67

	6.2	Browser	71
	6.3	Connecting to Bluetooth devices	80
	6.4	Connecting to a computer via USB	82
	6.5	Sharing your phone's mobile data connection	84
	6.6	Connecting to virtual private networks	85
7	Mul	timedia applications	87
	7.1	Camera	
	7.2	Gallery	
	7.3	You Tube	93
	7.4	Music	94
8	Goo	gle Maps	97
	8.1	Get My Location	
	8.2	Search for a location	
	8.3	Star a location	
	8.4	Get driving, public transport or walking directions	
	8.5	Arrangement of Layers	
	8.6	Join Latitude to see your friends' locations and	
		share yours with them	103
9	Oth	share yours with them ers	
9	Oth 9.1		
9		ers	107
9	9.1	e rs File Manager	107 107 107
9	9.1 9.2	ers File Manager Notes	107 107 107 108
9	9.1 9.2 9.3	ers File Manager Notes Sound Recorder	107 107 107 108 108
9	9.1 9.2 9.3 9.4	ers File Manager Notes Sound Recorder FM Radio	107 107 107 108 108 108 109
9	9.1 9.2 9.3 9.4 9.5	ers File Manager Notes Sound Recorder FM Radio Battery Saver	107 107 107 108 108 108 109 109
9	9.1 9.2 9.3 9.4 9.5 9.6	ers File Manager Notes Sound Recorder FM Radio Battery Saver Setup Wizard	107 107 108 108 108 109 109 109
9	9.1 9.2 9.3 9.4 9.5 9.6 9.7	ers File Manager Notes Sound Recorder FM Radio Battery Saver Setup Wizard Office suite	
9	9.1 9.2 9.3 9.4 9.5 9.6 9.7 9.8	ers File Manager Notes Sound Recorder FM Radio Battery Saver Setup Wizard Office suite Traffic Manager	107 107 108 108 108 109 109 109 110 110
9	9.1 9.2 9.3 9.4 9.5 9.6 9.7 9.8 9.9	ers	107 107 108 108 108 109 109 109 110 110 110
9	9.1 9.2 9.3 9.4 9.5 9.6 9.7 9.8 9.9 9.10	ers File Manager Notes Sound Recorder FM Radio Battery Saver Setup Wizard Office suite Traffic Manager Alcatel Help Voice Dailer	107 107 108 108 109 109 109 110 110 110 110
	9.1 9.2 9.3 9.4 9.5 9.6 9.7 9.8 9.9 9.10 9.11 9.12	ers File Manager Notes Sound Recorder FM Radio Battery Saver Setup Wizard Office suite Traffic Manager Alcatel Help Voice Dailer Voice Search	107 107 108 108 108 109 109 109 110 110 110 110 111
	9.1 9.2 9.3 9.4 9.5 9.6 9.7 9.8 9.9 9.10 9.11 9.12	ers	107 107 108 108 108 109 109 109 110 110 110 110 111 111 111

	10.2	Wireless & networks	13
	10.3	Call settings	16
	10.4	Audio profiles	18
	10.5	Display	19
	10.6	Location	20
	10.7	Security	22
	10.8	Applications	23
	10.9	Accounts & sync	26
	10.10	Privacy	27
	10.11	SD card & phone storage	28
	10.12	Language & keyboard	29
	10.13	Voice input & output	31
	10.14	Accessibility	33
	10.15	Date & time	34
	10.16	Schedule power on/off	34
	10.17	About phone	35
П	Mak	ing the most of your phoneI	37
	11.1	Android Manager	
	11.2	Upgrade	38
12	Tele	phone warrantyI	40
		essoriesI	
		ibleshootingI	
		-	
15	Spec	cificationsI	48



This product meets applicable national SAR limits of 2.0 W/kg. The specific maximum SAR values can be found on page 7 of this user guide.

When carrying the product or using it while worn on your body, either use an approved accessory such as a holster or otherwise maintain a distance of 1.5 cm from the body to ensure compliance with RF exposure requirements. Note that the product may be transmitting even if you are not making a phone call.

Safety and use.....

We recommend that you read this chapter carefully before using your phone. The manufacturer disclaims any liability for damage, which may result as a consequence of improper use or use contrary to the instructions contained herein.

• TRAFFIC SAFETY:

Given that studies show that using a mobile phone while driving a vehicle constitutes a real risk, even when the hands-free kit is used (car kit, headset...), drivers are requested to refrain from using their mobile when the vehicle is not parked.

When driving, do not use your phone and headphone to listen to music or to the radio. Using a headphone can be dangerous and forbidden in some areas.

When switched on, your phone emits electromagnetic waves that can interfere with the vehicle's electronic systems such as ABS anti-lock brakes or airbags. To ensure that there is no problem:

- do not place your phone on top of the dashboard or within an airbag deployment area,

- check with your car dealer or the car manufacturer to make sure that the dashboard is adequately shielded from mobile phone RF energy.

CONDITIONS OF USE:

You are advised to switch off the telephone from time to time to optimise its performance. Switch the phone off before boarding an aircraft.

Switch the phone off when you are in health care facilities, except in designated areas. As with many other types of equipment now in regular use, mobile telephones can interfere with other electrical or electronic devices, or equipment using radio frequency.

Switch the phone off when you are near gas or flammable liquids. Strictly obey all signs and instructions posted in a fuel depot, petrol station, or chemical plant, or in any potentially explosive atmosphere.

When the phone is switched on, it should be kept at least 15 cm from any medical device such as a pacemaker, a hearing aid or insulin pump, etc. In particular when using the phone, you should hold it against the ear on the opposite side to the device, if any.

To avoid hearing impairment, pick up the call before holding your phone to your ear. Also move the handset away from your ear while using the "hands-free" mode because the amplified volume might cause hearing damage.

Do not let children use the phone and/or play with the telephone and accessories without supervision.

When replacing the cover please note that your phone may contain substances that could create an allergic reaction.

Always handle your phone with care and keep it in a clean and dust-free place.

Do not allow your phone to be exposed to adverse weather or environmental conditions (moisture, humidity, rain, infiltration of liquids, dust, sea air, etc). The manufacturer's recommended operating temperature range is -10°C to +55°C.

At over 55° C the legibility of the phone's display may be impaired, though this is temporary and not serious.

Emergency call numbers may not be reachable on all cellular networks. You should never rely only on your phone for emergency calls.

Do not open, dismantle or attempt to repair your mobile phone yourself.

Do not drop, throw or bend your mobile phone.

Do not use the phone if the glass made screen, is damaged, cracked or broken to avoid any injury. Do not paint it.

Use only batteries, battery chargers, and accessories which are recommended by TCT Mobile Limited and its affiliates and are compatible with your phone model. TCT Mobile Limited and its affiliates disclaim any liability for damage caused by the use of other chargers or batteries.

Remember to make back-up copies or keep a written record of all important information stored in your phone.

Some people may suffer epileptic seizures or blackouts when exposed to flashing lights, or when playing video games. These seizures or blackouts may occur even if a person never had a previous seizure or blackout. If you have experienced seizures or blackouts, or if you have a family history of such occurrences, please consult your doctor before playing video games on your phone or enabling a flashing-lights feature on your phone.

Parents should monitor their children's use of video games or other features that incorporate flashing lights on the phones. All persons should discontinue use and consult a doctor if any of the following symptoms occur: convulsion, eye or muscle twitching, loss of awareness, involuntary movements, or disorientation. To limit the likelihood of such symptoms, please take the following safety precautions:

- Do not play or use a flashing-lights feature if you are tired or need sleep.
- Take a minimum of a 15-minute break hourly.
- Play in a room in which all lights are on.
- Play at the farthest distance possible from the screen.
- If your hands, wrists, or arms become tired or sore while playing, stop and rest for several hours before playing again.
- If you continue to have sore hands, wrists, or arms during or after playing, stop the game and see a doctor

When you play games on your phone, you may experience occasional discomfort in your hands, arms, shoulders, neck, or other parts of your body. Follow the instructions to avoid problems such as tendinitis, carpal tunnel syndrome, or other musculoskeletal disorders.

PROTECT YOUR HEARING

\$

To prevent possible hearing damage, do not listen at high volume levels for long periods. Exercise caution when holding your device near your ear while the loudspeaker is in use.

• PRIVACY:

Please note that you must respect the laws and regulations in force in your jurisdiction or other iurisdiction(s) where you will use your mobile phone regarding taking photographs and recording sounds with your mobile telephone. Pursuant to such laws and regulations, it may be strictly forbidden to take photographs and/or to record the voices of other people or any of their personal attributes, and duplicate or distribute them, as this may be considered to be an invasion of privacy. It is the user's sole responsibility to ensure that prior authorisation be obtained, if necessary, in order to record private or confidential conversations or take a photograph of another person; the manufacturer, the seller or vendor of your mobile phone (including the operator) disclaim any liability which may result from the improper use of the mobile phone.

• BATTERY:

Before removing the battery from your phone, please make sure that the phone is switched off. Observe the following precautions for battery use:

- Do not attempt to open the battery (due to the risk of toxic fumes and burns).
- Do not puncture, disassemble or cause a short-circuit in a battery.
- Do not burn or dispose of a used battery in household rubbish or store it at temperatures above 60°C.

Batteries must be disposed of in accordance with locally applicable environmental regulations. Only use the battery for the purpose for which it was designed. Never use damaged batteries or those not recommended by TCT Mobile Limited and/or its affiliates.



This symbol on your telephone, the battery and the accessories means that these products must be taken to collection points at the end of their life:



- Municipal waste disposal centres with specific bins for these items of equipment

- Collection bins at points of sale.

They will then be recycled, preventing substances being disposed of in the environment, so that their components can be reused.

In European Union countries:

These collection points are accessible free of charge.

All products with this sign must be brought to these collection points.

In non European Union jurisdictions:

Items of equipment with this symbol are not to be thrown into ordinary bins if your jurisdiction or your region has suitable recycling and collection facilities; instead they are to be taken to collection points for them to be recycled.

CAUTION: RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.

CHARGERS

Mains powered chargers will operate within the temperature range of: 0°C to 40°C.

The chargers designed for your mobile phone meet with the standard for safety of information technology equipment and office equipment use. They are also compliant to the ecodesign directive 2009/125/EC. Due to different applicable electrical specifications, a charger you purchased in one iurisdiction may not work in another iurisdiction. They should be used for this purpose only.

• RADIO WAVES:

Proof of compliance with international standards (ICNIRP) or with European Directive 1999/5/ EC (R&TTE) is required of all mobile phone models before they can be put on the market. The protection of the health and safety for the user and any other person is an essential requirement of these standards or this directive.

THIS DEVICE MEETS INTERNATIONAL GUIDELINES FOR EXPOSURE TO RADIO WAVES. Your mobile device is a radio transmitter and receiver. It is designed not to exceed the limits for exposure to radio waves (radio frequency electromagnetic fields) recommended by international guidelines. The guidelines were developed by an independent scientific organization (ICNIRP) and include a substantial safety margin designed to assure the safety of all persons, regardless of age and health.

The radio wave exposure guidelines use a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit for mobile devices is 2 W/kg.

Tests for SAR are conducted using standard operating positions with the device transmitting at its highest certified power level in all tested frequency bands. The highest SAR values under the ICNIRP guidelines for this device model are:

Maximum SAR for this model and conditions under which it was recorded.			
Head SAR	UMTS 2100 + Wi-Fi + Bluetooth	0.848 W/kg	
Body-worn SAR	GSM 900 + Wi-Fi + Bluetooth	0.709 W/kg	

During use, the actual SAR values for this device are usually well below the values stated above. This is because, for purposes of system efficiency and to minimize interference on the network, the operating power of your mobile device is automatically decreased when full power is not needed for the call. The lower the power output of the device, the lower its SAR value.

Body-worn SAR testing has been carried out at a separation distance of 1.5 cm. To meet RF exposure guidelines during body-worn operation, the device should be positioned at least this distance away from the body. If you are not using an approved accessory ensure that whatever product is used is free of any metal and that it positions the phone the indicated distance away from the body.

Organizations such as the World Health Organization and the US Food and Drug Administration have stated that if people are concerned and want to reduce their exposure they could use a hands-free device to keep the phone away from the head and body during phone calls, or reduce the amount of time spent on the phone.

For more information you can go to www.alcatelonetouch.com

Additional information about electromagnetic fields and public health are available on the following site: http://www.who.int/peh-emf.

Your telephone is equipped with a built-in antenna. For optimal operation, you should avoid touching it or degrading it.

As mobile devices offer a range of functions, they can be used in positions other than against your ear. In such circumstances the device will be compliant with the guidelines when used with headset or usb data cable. If you are using another accessory ensure that whatever product is used is free of any metal and that it positions the phone at least 1.5 cm away from the body.

• LICENCES



microSD Logo is a trademark.

The Bluetooth word mark and logos are owned by the Bluetooth SIG, Inc. and any use of such marks by TCT Mobile Limited and its affiliates is under license. Other trademarks and trade names are those of their respective owners.

ONE TOUCH 4010X/4010D Bluetooth QD ID B020261



TouchPalTM and CooTekTM are trademarks of Shanghai HanXiang (CooTek) Information Technology Co., Ltd. and/or its Affiliates.



SwiftKey is a registered trademark of TouchType Ltd.



The Wi-Fi Logo is a certification mark of the Wi-Fi Alliance.

Google, the Google logo, Android, the Android logo, Google Search [™], Google Maps[™], Gmail [™], YouTube, Android Market, Google Latitude [™] and Google Talk [™] are trademarks of Google Inc.

Regulatory information

The following approvals and notices apply in specific regions as noted.

4010X:



T Mobile Europe SAS - Siège social : 55 Avenue des Champs Pierreux, Immeuble Le Capitole 92000 Nanterre Franc SAS au capital de 23 031 072 euros - RCS Nanterre B 440 038 222 - Siret 440 038 222 000 38 APE 4652Z

4010D:



55 Avenue des Champs Pierreux, Immeuble Le Capitole 92000 Nanterre, France +33 1 46 52 61 00

Product / Produi WiFi and FM ra FM	EC declaration of conformity / Déclaration de conformité CE I: SBPAHSUPAUNTS due land / GSM quad bands handhald station with buetoch technology, ti SBPAHSUPAUNTS buend / GSM quadribandes avec technologie Bluetoch, Wifi et radio dio / Portatif HSDPA/HSUPA/UMTS bibande / GSM quadribandes avec technologie Bluetoch, Wifi et radio
Product identif	ication / Identification du produit : ALCATEL ONE TOUCH 4010D type Beetle Lite 2SIM EU
We / Nous	TCT Mobile Europe SAS 55, avenue des Champs Pierreux 92001 Nanterre
requirements assessment p dessus est en	France our sole responsibility that the product above menioned is conform to the applicable essential of the directive 1999/SFC and that all essential radio test suites have been carried out. Conformity rocedure : annew 17 time directive. / Indirective a source note entitive responsability (see la produit de productive intervention) and and the source of the source of the source of the source of the radio essentiveles ont étée effectives. Procedure d'evaluation de conformité : anneve 17 de la
 Item 3.1.a la sécur 	dards / Normes appliquées : (protection of the health and of the safety of the user) / Article 3.1.a (protection de la santé et de lié de / luitilisature EN 60560-12006 + A11:2006 + A1:2010 + A12:2011 EN 622064 / 2006 / A11:2008 + A1:2010 + A12:2011
- Item 3.1.b de prote	EN 82302 (2010) EN 93 032. 20170) IN 93 032. 20170/A22006, Council recommendation 1999/619/EC (July 99) (protection explainments with respect to electromagnicus compatibility) / Article 3.1.b (exigences citican en ca qui concent la compatibility EN 901 493-1 v1.9.2 (2011-90, EN 901 493-3.1.4.1 (2002-90, EN 901 486-7 v1.3.1 (2005-11), v2.1.1 (2006-96, IN 901 495-2 v1.4.1 (2011-10)
 Item 3.2 (spectre 	V.2. 11 (2009-05), EN SUI 499-24 V1.51 (2010-10) effective use of spectrum so as to avoid harmful interferences // Article 3.2 (utilisation efficace du radiolectrique de façon à éviter les interferences dommageables) EN 301 511 V.9.2 (2009-03), EN 301 906-14. 5.2.1 (2011-05), EN 301 908-2 v.5.2.1 (2011-07) , EN 300 328 v.1.7.1 (2008-10), EN 300 440-1 v1.6.1 (2010-08), EN 300 440-2 v1.4.1(2010-08)
This product avec la direc	also conforms to the applicable requirements of following directives, / Ce produit est en conformité tive,
2004/108/EC (co - EN	004/108EC (electromagnetic compatibility). / Ce produit est en conformité avec la directive mytebilité décomagnétique) 55013-2001 +4/2-2006
	55020:2007 11/65/EU (RoHS - restriction of the use of certain hazardous substances)
This product c (Ce produit pe suivants :)	an connect with a Common Mobile Phone Charger which complies with below standards: ut être utilisé avec un chargeur universel pour téléphone portable conforme aux standards
1	EN301 489-34 v1.1.1 (2010-10), EN301 489-34 v1.3.1 (2012-05) EN 62684:2010
conformité de ce American Ce	this product has been reviewed by the following Notified body of directive 1999/5/EC / La produit a 46 vérifiée par l'organisme de certification (notify body) suivant. tification Body, Inc.
	Whittler Avenue 6731, 22101 McLean, Virginia, United States C€1588
Date :2013-0 Signature	3-12 Christophe Benoit
TCT M	Abbile Europe SAS / Deptity General Manager, EMEA.
	*1

TCT Mobile Europe SAS - Siège social : 55 Avenue des Champs Pierreux, Immeuble Le Capitole 92000 Nanterre France SAS au capital de 23 031 072 euros - RCS Nanterre B 440 038 222 - Siret 440 038 222 000 38 APE 4652Z

General information

- Internet address: www.alcatelonetouch.com
- Hot Line Number: see "TCT Mobile Services" leaflet or go to our website.
- Address: Room 1910-12A, Tower 3, China HK City, 33 Canton Road, Tsimshatsui, Kowloon, Hong Kong

On our website, you will find our FAQ (Frequently Asked Questions) section. You can also contact us by email to ask any questions you may have.

An electronic version of this user guide is available in English and other languages according to availability on our server:

www.alcatelonetouch.com

Your telephone is a transceiver that operates on GSM/GPRS/EDGE in quad-band with 850/900/1800/1900 MHz or UMTS in dual-band with 900/2100 MHz.

C€1588

This equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. The entire copy of the Declaration of Conformity for your telephone can be obtained through our website: www.alcatelonetouch.com.

Protection against theft⁽¹⁾

Your telephone is identified by an IMEI (phone serial number) shown on the packaging label and in the phone's memory. We recommend that you note the number the first time you use your telephone by entering * # 0 6 # and keep it in a safe place. It may be requested by the police or your operator if your telephone is stolen. This number allows your mobile telephone to be blocked preventing a third person from using it, even with a different SIM card.

Disclaimer

There may be certain differences between the user manual description and the phone's operation, depending on the software release of your telephone or specific operator services.


TCT Mobile shall not be held legally responsible for such differences, if any, nor for their potential consequences, which responsibility shall be borne by the operator exclusively.


⁽I) Contact your network operator to check service availability.

This handset may contain materials, including applications and software in executable or source code form, which is submitted by third parties for inclusion in this handset ("Third Party Materials"). All third party materials in this handset are provided "as is", without warranty of any kind, whether express or implied, including the implied warranties of merchantability, fitness for a particular purpose or use/third party application, interoperability with other materials or applications of the purchaser and non-infringement of copyright. The purchaser undertakes that TCT Mobile has complied with all quality obligations incumbent upon it as a manufacturer of mobile devices and handsets in complying with Intellectual Property rights, TCT Mobile will at no stage be responsible for the inability or failure of the Third Party Materials to operate on this handset or in interaction with any other devices of the purchaser. To the maximum extent permitted by law, TCT Mobile disclaims all liability for any claims, demands, suits or actions, and more specifically - but not limited to - tort law actions, under any theory of liability, arising out of the use, by whatever means, or attempts to use, such Third Party Materials. Moreover, the present Third Party Materials, which are provided free of charge by TCT Mobile, may be subject to paid updates and upgrades in the future; TCT Mobile waives any responsibility regarding such additional costs, which shall be borne exclusively by the purchaser. The availability of the applications may vary depending on the countries and the operators where the handset is used; in no event shall the list of possible applications and software provided with the handsets be considered as an undertaking from TCT Mobile; it shall remain merely as information for the purchaser. Therefore, TCT Mobile shall not be held responsible for the lack of availability of one or more applications wished for by the purchaser, as its availability depends on the country and the operator of the purchaser. TCT mobile reserves the right at any time to add or remove Third Party Materials from its handsets without prior notice; in no event shall TCT Mobile be held responsible by the purchaser for any consequences that such removal may have on the purchaser regarding the use or attempt to use such applications and Third Party Materials.

Your mobile.....

I.I Keys and connectors





- On Home screen, press to quickly access Settings menu or Notification panel; to launch quick search; to manage applications; to customize your Home screen by adding applications or changing wallpaper.
 - On other screens, press to view options list.
- Press: Return to the Home screen or back to the central Home screen if it is extended.

Press and hold: Enter the recently used applications list.

- Go back to the previous menu or screen.
 - Press: Lock the screen. Light up the screen.

Press and hold: When phone is off, power on the phone. When phone is on, enter Phone options: Silent mode, Airplane mode, Power off.

Press to adjust the Volume (in call/media playing mode)

I.2 Getting started


I.2.I Set-up

Removing or installing the back cover



Inserting or removing the SIM card⁽¹⁾

You must insert your SIM card to make phone calls. Please power off your phone and remove battery before inserting or removing the SIM card.



Place the SIM card with the chip facing downwards and slide it into its housing. Make sure that it is correctly inserted. To remove the card, press and slide it out.


⁽¹⁾ Check with your network operator to make sure that your SIM card is 3V or 1.8V compatible. The old 5 volt cards can no longer be used.

Installing or removing the battery



- Insert and click the battery into place, then close the phone cover.
- Unclip the cover, then remove the battery.

Installing and removing the microSD card



To release the microSD card holder, slide it in the direction of the arrow and lift it. Then insert the microSD card with the golden contact downward. Finally, turn down the microSD holder and slide it in the opposite direction to lock it.

Charging the battery



Connect the battery charger to your phone and mains socket respectively.

- The LED light will be lit up during battery charging.
- · Be careful not to force the plug into the socket.
- Make sure the battery is correctly inserted before connecting the charger.
- The mains socket must be near to the phone and easily accessible (avoid electric extension cables).
- When using your telephone for the first time, charge the battery fully (approximately 4 hours).

You are advised to fully charge the battery (
). Charging status is indicated by the depth of water on the lock screen. The depth increases as the phone is charged.

ڳ

To reduce power consumption and energy waste, when battery is fully charged, disconnect your charger from the plug; switch off Wi-Fi, GPS, Bluetooth or background-running applications when not in use; reduce the backlight time, etc.

1.2.2 Power on your phone

Hold down the **Power** key until the phone powers on, type in your PIN code if necessary and then confirm. The Home screen is displayed.

If you do not know your PIN code or if you have forgotten it, contact your network operator. Do not leave your PIN code with your telephone. Store this information in a safe place when not in use.

Set up your phone for the first time

The first time you power on the phone, you're are prompted to set up your phone in multiple ways: language, input method, mobile data connection, account setup and synchronization, system update, etc. You are required to sign into your Google account to synchronize email, contacts, calendar and other Google applications ⁽¹⁾.

- Enter your user name and password, then touch Sign in. If you forget your password, you can go to http://www.google.com/ to retrieve it. If you don't own a Google Account, you are prompted to create one by touching Create.
- Read the setup information on the screen.
- Mark/Unmark the check box to choose whether you want to take advantage of Google's location service, then touch **Next**.
- Mark/Unmark the check box to choose whether you want to back up data with your Google account, then touch **Next**.
- Touch Finish setup.

This initial set up can be skipped and enabled via **Settings** Accounts & sync.

In power on screen without SIM card inserted, you can also connect to a Wi-Fi network (refer to section 6.1.2 Wi-Fi) to sign into your Google account and to use some features.

For dual SIM model, the first time you insert a new SIM card, you are given the option to change the default SIM settings (refer to section 10.1 SIM management).

1.2.3 Power off your phone

Hold down the **Power** key until the phone options appear, select **Power off**.

I.3 Home screen

You can bring all the items (applications, shortcuts, folders and widgets) you love or use most frequently to your Home screen for quick access. Press **Home** key to switch to Home screen.



Home screen is provided in an extended format to allow more space for adding applications, shortcuts etc. Slide the Home screen horizontally left and right to get a complete view of the Home screen. Small dots at the lower left and right of the screen indicate which screen you are viewing.

I.3.1 Using the touchscreen

Touch

To access an application, touch it with your finger.

¹⁾ Application availability depends on country and operator.

Touch and Hold

To enter the available options for an item, touch and hold the item. For example, select a contact in Contacts, touch and hold this contact, options list will then appear on screen.

Drag

Place your finger on the screen to drag an object to another location.

Slide/Swipe

Slide the screen to scroll up and down the applications, images, web pages... at your convenience. You could slide the screen horizontally too.

Flick

Similar to swiping, but flicking makes it move quicker.

Pinch/Spread

Place your fingers of one hand on the screen surface and draw them apart or together to scale an element on the screen.

Rotate

Automatically change the screen orientation from portrait to landscape by turning the phone sideways to have a better screen view.

1.3.2 Status bar

From status bar, you can view both phone status (to the right side) and notification information (to the left side). When the status bar is full, " ricon will appear, touch to display hidden icons.

Status icons

For dual SIM model, status icons referring to either SIM1 or SIM2 will be identified by a colour which you have defined.

tt G	GPRS connected	Ó	Receiving location data from GPS
ti G	GPRS in use	G	Speakerphone is on
ti E	EDGE connected	Bat	Roaming
È	EDGE in use	١١	No signal
** 36	3G connected		Vibrate mode
다. 35	3G in use	∎×	Silent mode
↑ H	HSPA (3G+) connected	₽×	Phone microphone is mute
Ħ	HSPA (3G+) in use	Ĺ	Battery is very low
	Connected to a Wi-Fi network		Battery is low
*	Bluetooth is on		Battery is partially drained
*	Connected to a Bluetooth device		Battery is full
齫	Airplane mode	۶	Battery is charging
$\overline{\mathbb{O}}$	Alarm is set	Q	Headset connected
¢	GPS is on and in use	all.	Signal strength

Notification icons

\square	New Gmail message	6	Call in progress (green)
Ÿ	New text or multimedia message	٢	Call in progress using Bluetooth headset (blue)
P	Problem with text or multimedia message delivery	ň	Missed call
ţalk	New Google Talk message	G	Call on hold
00	New voice mail	C.	Call forwarding is on
1	Upcoming event	<u>†</u>	Uploading data
Ð	Data is synchronizing	Ŧ	Downloading data
Ð	Problem with sign-in or synchronization	(h-	An open Wi-Fi network is available
. 0!	microSD card is full	ψ	Phone is connected via USB cable
0-	Connected to or disconnected from VPN	FM	Radio is on
	Song is playing	¥	System update available
÷	USB tethering is on	?	Portable Wi-Fi hotspot is on
\odot	Both USB tethering and portable hotspot are on	Â	Application update available

Notification panel

Touch and drag down the Status bar or press **Menu** key and touch **Notifications** to open the notification panel. Touch and drag up to close it. From the Notification panel, you can open some functions by touch (GPS, Bluetooth, etc.), reminders indicated by notification icons, or view wireless service information.

August 18, 2011 🛛 🔛 🚮 💼 15:05
ବ 🖇 🔮 🖪 🛧
Wi-Fi Bluetooth GPS Data Airplane
SIM1 Operator
SIM2 Operator
Ongoing
USB connected Select to copy files to/from your computer.
USB debugging connected Select to disable USB debugging.
Notifications
2 missed calls 10:48

Touch clear all event-based notifications (other ongoing notifications will remain).

1.3.3 Search bar

The phone provides a Search function which can be used to locate information within applications, the phone or the web.



Search by text

- Touch Search bar from Home screen or press **Search** key from other applications screen.
- Enter the text/phrase you want to search for. A list of search results will be displayed for you to select from.
- Touch Go to search the web.

Search by voice

- Speak the word/phrase you want to search for. A list of search results will display for you to select from.

I.3.4 Lock/Unlock your screen

To protect your phone and privacy, you can lock the phone screen by creating a variety of patterns, PIN or password etc.

To create a screen unlock pattern (refer to section 10.7.1 for detailed settings)

- Press Menu key from the home screen, touch Settings, then touch Security/Set up screen lock/Pattern.
- Draw your own pattern, you can also press **Menu** key for help.



To create a screen unlock PIN/Password

- Press Menu key from the home screen, touch Settings, then touch Security/Set up screen lock/PIN or Password.
- Set your PIN or password.

To lock phone screen

Press Power key once to lock the screen.

To unlock phone screen

Draw the unlock pattern you have created or enter PIN or password to wake up the screen. If you did not set the unlock screen, drag down the lock icon to unlock it.



1.3.5 Personalize your home screen

Add

Touch and hold an empty area or press **Menu** key and touch **Add** on the Home screen. The **Add to Home screen** will appear, offering a range of options.

- Shortcuts To add a shortcut to Home screen, such as applications, bookmark, contact, etc.
- Widgets To add a widget to Home screen, such as clock, music player, etc.
- Folders To add a folder to Home screen, such as new folder, contact folder, etc.

To improve the organization of the Home screen items (shortcuts, widgets), you can add them to a folder by touching and dragging them onto the folder of your choice. To rename a folder, open it, touch and hold the folder's title bar to open the Rename folder dialog box, then enter the new folder name and confirm with **OK**.

Reposition

Touch and hold the item to be repositioned to activate the Move mode, drag the item to the desired position and then release. Hold the icon on the left or right edge of the screen to drag the item to another Home screen page.

Remove

Touch and hold the item to be removed to activate the Move mode, drag the item to the bottom trash can, which will then turn red, and release.

Wallpaper customization

Touch and hold an empty area or press **Menu** key and touch **Wallpapers** on the Home screen, a popup window named **Select wallpaper from** will appear, offering a range of options. **Gallery** includes pictures you have taken, cropped or downloaded. **Live wallpapers** include a scrolling list of animated wallpapers to choose from. **Wallpaper gallery** includes all preset wallpapers in the phone. Slide left and right to locate a desired image, touch **Set wallpaper** to confirm.

I.3.6 Application tab

Touch in Home screen to enter applications list.

To return to the Home screen, press Home key.

Consult recently-used applications

To consult recently-used applications, you can press and hold the **Home** key. Touch an icon in the window to open the related application.

Jar Music

1.3.7 Volume adjustment

Press **Volume up/down** key to adjust the volume. While in the lowest volume level, your phone will be switched to vibrate/silent mode⁽¹⁾.

⁽I) The phone setting will vary depending on the changes made to the general settings in Settings\Audio profiles\Silent.

2 Text input

2. I Using Onscreen Keyboard

Onscreen keyboard will display automatically when a program requires entering text or numbers.


Onscreen keyboard settings

Press Menu key from Home screen, select Settings\Language & keyboard, a series of settings are available for your selection.

Adjust the onscreen keyboard orientation

Turn the phone sideways or upright to adjust the onscreen keyboard orientation. You can also adjust it by settings (Press **Menu** key on **Home screen****Settings\Display**).

2.1.1 Android keyboard



2.2 Text editing

Touch the text you have entered to make an edit.

- Touch and hold the text field to zoom in on the text with a magnifying glass.
- Touch twice the text you have entered and then touch **Select all/Select** word in the pop up button.
- The selected text is now highlighted in orange. Drag a selection tab under to adjust the range of selected text.
- Touch **Cut/Copy/Paste** ⁽¹⁾ in the pop up button.

⁽¹⁾ **'Paste'** option will not appear unless copy or cut operation has been made.

3 Phone call, Call log and Contacts

3. Phone

3.1.1 Placing a call

The user can easily start a call using **Phone**.

Enter this menu using one of the following two ways:

- Touch 📞 from Home screen.
- Touch from Home screen and select **Phone.**



Enter the desired number from keyboard directly or select a contact from **Contacts, Call log** or **Favourites** by touching tabs, then touch to place the call. The number you entered can be saved to **Contacts** by touching **(a)**.

If you make a mistake, you can delete the incorrect digits by touching 💌

To hang up a call, touch End.

International call

To dial an international call, touch and hold $\boxed{0}$ to enter "+", then enter the international country prefix followed by the full phone number and finally touch \boxed{C} .

Emergency call

If your phone has network coverage, dial emergency number and touch to make an emergency call. This works even without a SIM card and without typing the PIN code.

3.1.2 Answering or rejecting a call



When you receive an incoming call, touch the green phone icon to answer; touch the red phone icon to reject.

When you receive an incoming call, but don't want to answer, you may decline it by dragging up the red phone icon. The caller is sent directly to your voice mail box to leave a message. Or to reject a call with an SMS, by pressing the **Menu** key and touching **Send message**.

3.1.3 Calling your voice mail

Your voice mail is provided by your network to avoid missing calls. It works like an answering machine that you can consult at any time.

To access your voice mail, touch and hold 1 on Phone tab.

To set your voice mail number, enter **Settings\Call settings\Voice call**\ **Voice mail**.

If you receive a voice mail, a voice mail icon ∞ appears on the Status bar. Open the Notification panel, touch **New voice mail**.

3.1.4 During a voice call

When a call is in progress, press **Menu** key to open the call options. Touch **Bluetooth** to switch between headset and phone or touch **Start recording** to record the call. To adjust the volume during a call, press **Volume up/down** key.



- Touch to hold the current call. Touch this icon again to retrieve the call.
 - Touch to mute the current call. Touch this icon again to unmute the call.
- Touch to activate the speaker during the current call. Touch this icon again to deactivate the speaker.
- Touch to access **Contacts** or call a contact.
- Touch to add a caller by entering their phone number.
- Touch to display Dialpad.
- Touch to end the current call.
 - To avoid misoperation on touchscreen during call, screen will be locked automatically when user put the phone close to ear, and it will be unlocked when put the phone away.

3.1.5 Managing multiple voice calls

With this phone you can handle multiple voice calls at the same time.

Swap calls

1

When you have accepted two calls, touch **Swap** to alternate between them. You can now switch between two lines. The current call is put on hold and you have joined in the other call.

Conference calls (1)

You can set up a conference call.

- Place a call to the first participant of the conference call.
- Touch 🔁 to add another call.
- Touch Merge calls to start the conference call.
- During a conference call, touch (b) to drop a participant or to talk privately to one of the participants. Touch **End** to drop the participant from the conference, touch **Private** to talk privately to the participant and hold on other participants.
- Touch to end the conference call and disconnect all callers.

3.2 Call log......



You can access your call memory by touching **m** from the Home screen and touching **Call log**. Touch contact/number to place a call directly. There are three kind of calls in Call log:

R/	Missed calls	
K.	Incoming calls	
	Outgoing calls	

Touch AII, W, I, I to view the call types sorted by: All calls, Missed calls, Outgoing calls or Incoming calls. You can also touch to view calls sorted by All resources, SIMI, SIM2 or Internet.

Touch O or touch and hold a contact/number to view information or further operations.

You can view detailed information of a call, launch a new call or send message to a contact/number, or add number to **Contacts** (only available for phone numbers), etc.

To clear the entire call memory, press $\ensuremath{\textbf{Menu}}$ key then touch $\ensuremath{\textbf{Clear call}}$ log.

To set speed dial, press Menu key then touch Set speed dial.


3.3 Contacts.....

Contacts enables quick and easy access to the people you want to reach.

You can view and create contacts on your phone or either SIM and synchronize these with your Gmail contacts or other applications on the web or on your phone.

3.3.1 Consult your Contacts

To access the **Contacts**, touch **m** on the Home screen, then select **Contacts**.



Touch and hold a contact to display its option menu. You can also press **Menu** key to display contacts list option menu.

Following actions are enabled:

- Search Touch to search for a contact.
- Groups Assign contacts to groups so that one SMS/MMS or email can easily be sent to all members.
- Set speed dial Add a contact's phone number as a speed dial number. Digits 2 to 9 are available.
- New contact Add new contact.


More\Sync

- Delete contact Select and delete unwanted contacts.
- More\Import/ Import or export contacts between phone, SIM Export card, and microSD card.
- More\Display Choose contacts to display, for example only options
 contacts with phones, other application contacts if any, etc.
- More\Accounts Manage the synchronization settings for different accounts.
 - Synchronize contacts from other account like Google, Facebook, etc. to your Contacts.
- More\Share visible Share contacts with others by sending the contacts contact's vCard to them via Bluetooth, SMS, Email, etc.

3.3.2 Adding a contact

Press Menu key from contacts list screen and touch New contact. You're required to select the location (Phone/SIM1/SIM2) to save the contact.

You are required to enter the contact's name and other contact information. By scrolling up and down the screen, you can move from one field to another easily.



When finished, touch **Done**.

Add to/remove from Favourites

To add a contact to favourites (only available for phone contacts), touch and hold a contact to display the contact's option menu, then touch **Add to Favourites**. Or you can also touch a contact to view details then touch to add the contact to favourites (the star will turn gold in color).

To remove a contact from favourites, select **Remove from Favourites** on the contact's option menu or touch gold star \ge on contact details screen.

3.3.3 Editing your contacts

To edit contact information, touch and hold the contact whose information is to be edited, then touch **Edit contact**. When finished, touch **Done**.

Change a contact's default phone number

The default phone number (the number which has priority when making a call or sending a message) will always be displayed under the contact name. To change the default phone number, touch and hold the number you want to set as the default number from the contact's details screen, then select **Make default number**. A \checkmark appears after the number.

Block incoming calls/Set ringtone for a contact

On the contact's detail screen, press **Menu** key to display contacts list option menu, and touch **Options**, then select **Incoming calls** or **Ringtone**.

When one contact has been set to block incoming calls directly, if he/she calls, your phone doesn't ring and the caller will be sent directly to your voice mail.

Delete a contact

To delete a contact, press **Menu** key and touch **Delete contact** from contact details screen or directly touch and hold a contact from Contacts screen to display contacts list option menu then touch **Delete contact**. Touch **OK** to confirm.

نې

The contact you have deleted will also be removed from other applications on phone or web the next time you synchronize your phone. A contact deleted from SIM1/SIM2 cannot be reinstated.

3.3.4 Communicating with your contacts

From the contacts list, you can communicate with your contacts by making a call or exchanging messages.

To launch a call from contact's details screen, touch and hold the number you want to call, then touch Call contact.You can also touch ${\bf C}$.

To send a message using a contact's details screen, touch and hold the number you want to send a message to, then touch **Send text message**. You can also touch \blacksquare on the right side.

Use Quick contact for Android

Touch a contact's picture to open Quick Contact for Android, you can touch the icon for the way you want to connect.



The icons available on Quick Contact bar depend on the information you have for the contact and the applications and accounts on your phone.

3.3.5 Contacts importing, exporting and sharing

This phone enables you to import contacts from SIM card/microSD card and export contacts to a microSD card which can then be used to back up your information.

From Contacts screen, press **Menu** key to open the contacts list option menu,touch **More\Import/Export**. From here you can exchange contacts between Phone and SD card; Phone and SIM card; SIM1 and SIM2, using the following steps:

- Select the location that you want to copy the contacts from, then touch Next.
- Select the location that you want to copy the contacts to, then touch Next.
- Touch the contact you want to copy, or mark the **Select all** check box, then touch **Copy** to confirm.

You can share a single contact or contacts with others by sending the contact's vCard to them via Bluetooth, SMS, Email, etc.

Touch a contact you want to share, press **Menu** key and touch **Share** from contact details screen, then select the application to perform this action.

3.3.6 Displaying contacts

You can configure which groups of contacts, for each account, you want to display in the Contacts list. To hide/display contacts that don't have phone numbers, press **Menu** key from contacts list screen, touch **More\Display options**, then activate or deactivate **Only contacts with phones** by touching it. Finally, touch **Done**. The same operation for other options: **Phone Contacts, SIM contacts, Sort list by, View contact names as**.

3.3.7 Joining/Separating contacts

To avoid duplication, you can add any new contact information to existing contacts in a single action (only available for phone contacts).

Touch the contact which you want to add information to, press **Menu** key and touch **Edit contact**, then press **Menu** key again and touch **Join**.

At this time, you are required to select the contact whose information you want to join with the first contact. The information from the second contact is added to the first one, and the second contact will no longer be displayed in the Contacts list.

To separate contact information, touch the contact whose information you want to separate, press **Menu** key and touch **Edit contact**, then press **Menu** key again and touch **Separate**.

3.3.8 Accounts

Contacts, data or other information can be synchronized from multiple accounts, depending on the applications installed on your phone.

To add an account, press **Menu** key from Contacts list, touch **More Accounts**, then touch **Add account** tab; or access it by pressing **Menu** key from Home screen, touch **Settings**, then selecting **Accounts & Sync** and finally touching **Add account** tab.

You are required to select the kind of accounts to add, like Google, Facebook, etc.

As with other account set-ups, you need to enter detailed information, like username, password, etc.

You can remove an account to delete it and all associated information from the phone.

Open the **Accounts & sync settings** screen, touch the account you want to delete, then press **Menu** key and touch **Remove account** and confirm.

Useful icons:



Indicates that the account is configured to synchronize automatically with your phone.



Indicates that the account is not configured to synchronize automatically with your phone.

Background data

Activate or deactivate **Background data** to control whether applications or services data can be transmitted when they are running in the background. Applications can synchronize, send, and receive data at any time if activated.

Auto-sync

When activated, all changes to information on the phone or online will be automatically synchronized to each other.

Sync manually

You can synchronize an account manually on **Accounts & sync settings** screen, and you must touch an account in the list on this screen, touch **Sync now**.

Google Messaging, Gmail/ Email, Google Talk

Google Messaging 4.1

You can create, edit and receive SMS and MMS with this mobile phone.

To access this feature, touch in from Home screen, then select Messaging.



4.1.1 Write message

On message list screen, touch Compose new message to write text/ multimedia messages.



Sending a text message

Enter mobile phone number of the recipient on **To** bar or touch and to add recipients, touch **Type to compose** bar to enter the text of the message. When finished, touch **Send** to send the text message. For dual SIM model, touch **Send** to select the SIM card for sending.

An SMS message of more than 160 characters will be charged as several SMS. A counter will always appear on the top right corner of the text box to remind you how many characters are allowed to be entered in one message.



Specific letters (accent) will increase the size of the SMS, this may cause multiple SMS to be sent to your recipient.

Sending a multimedia message

MMS enables you to send video clips, images, photos, animations, slides and sounds to other compatible mobiles and email addresses.


An SMS will be converted to MMS automatically when media files (image, video, audio, slides, etc.) are attached; Subject or email addresses added.

To send a multimedia message, enter the recipient's phone number in the To bar, touch Type to compose bar to enter the text of the message. Press Menu key to open the option menu, touch Add subject to insert a subject, and touch Attach to attach picture, video, audio or slide. When finished, touch Send to send the multimedia message. For dual SIM model, touch **Send** to select the SIM card for sending.

Attach options:

Pictures	Access Gallery application/File Manager to select a picture as attachment.
Capture picture	Access Camera to capture a new picture for attaching.
Videos	Access Gallery application/File Manager to select a video as attachment.
 Capture video 	Access Camcorder to record a new video for attaching.
Audio	Access to select an audio file as attachment.
Record audio	Enter Sound recorder to record a voice message for attaching.

• Slideshow Enter Edit slideshow screen, touch Add slide to create a new slide, and touch currently existing slide to edit it (see following picture). Press Menu key to get more actions, like setting the slide duration, adding music, etc.



4.1.2 Manage messages

When receiving a message, an icon \swarrow will appear on status bar as notification. Drag down the status bar to open Notification panel, touch the new message to open and read it. The SIM name on the lower right corner indicates which SIM card received/sent the message. You can also access the Messaging application and touch the message to open.

Messages are displayed in conversational order.

To reply to a message, touch the current message to enter message composing screen, enter the text, then touch **Send**. For dual SIM model, touch **Send** to select the SIM card for sending.

To return to the message list from a text message thread, press **Menu** key and then touch **More\All threads**.

Touch and hold a message in message details screen. The following message options are available for selection:

Lock/Unlock message	Touch to lock/unlock the message so it can/can't be deleted if you reach maximum number of stored messages.
Call	Call the sender's number.
Add to Contacts	Add the number to Contacts.
Add to Bookmark	Add the number to bookmark.
Forward	Touch to forward the message to another recipient.
Copy message text	Copy the current message content. You can paste it to the enter bar of the new message you are going to compose.
Save message to SIM card	Touch to save the SMS to the SIM card.
View message details	Touch to view details of the message.
Delete message	Delete the current message.

4.1.3 Adjust message settings

You can adjust a set of message settings. From Messaging application screen, press **Menu** key and touch **Settings**.

Storage settings

center

- Delete old Select to delete old messages when the maximum number of stored messages is reached.
- Text message limit Touch to set number of text messages to save.
- Multimedia Touch to set number of multimedia messages to message limit save.

Text message (SMS) settings

- Delivery reports Select to request a delivery report for each text message you send.
 Manage SIM Touch to manage text messages stored on your SIM card.
 Validity period Touch to set validity period for text messages.
 Edit quick text Touch to add custom quick text.
 SMS Service Touch to view service center number.
- SMS storage Touch to set SMS storage location in Phone or location

Multimedia message (MMS) settings

- Delivery reports Select to activate it, then you can touch Menu key from a multimedia message thread, and touch View report to check delivery status.
- Read reports Select to request a report on whether each recipient has or has not read a multimedia message sent by you.
- Send read reports Select to send a read report if requested by the sender.
- Auto-retrieve Select to download the full MMS message (including message body and attachment) automatically to your phone. Otherwise, download only the MMS message header.
- Roaming autoretrieve
 Select to download the full MMS message (including message body and attachment) automatically when roaming. Otherwise, download only the MMS message header to avoid extra charges.
- Creation mode Touch to set MMS creation mode when composing message.
- Maximum Touch to set maximum message size.
- Priority Touch to set MMS priority.

Notification settings

- Notifications Select to display message notifications in status bar.
- Select ringtone Touch to select a ringtone as a new message notification tone.

Service message setting

• Enable service Select to enable to receive service message.

4.2 Gmail/Email

The first time you set up your phone, you can select to use an existing Gmail or to create a new Email account.



4.2.1 Gmail

As Google's web-based email service, Gmail is configured when you first set up your phone. Gmail on your phone can be automatically synchronized with your Gmail account on the web. Unlike other kinds of email account, each message and its replies in Gmail are grouped in your inbox as a single conversation; all emails are organized by labels but not by folders.

To access Gmail

From Home screen, touch **m** to enter the applications list, then touch **Gmail**.

Gmail displays messages and conversations from one single Gmail account at a time, if you own more than one account, you can switch to another by pressing **Menu** key from Inbox screen, touching **Accounts**, then touching the account you want to view.

To create and send emails

- Press Menu key from Inbox screen, and touch Compose.
- Enter recipient(s)'s email address in **To** field, and if necessary, press **Menu** key and touch **Add Cc/Bcc** to include a copy or a blind copy to the message.
- Enter the subject and content of the message.
- Press Menu key, touch Attach to send an attachment to the receiver.
- Finally, touch Send.
- If you do not want to send the mail out right away, you can touch save copy. To view the draft, press Menu key and touch Go to labels, then select Drafts.

 If you do not want to send or save the mail, you can press Menu key and then touch Discard.

To add a signature to emails, press **Menu** key from inbox screen, and touch **More\Settings\Account settings**, then select **Signature**.

To receive and read your emails

When a new email arrives, you will be notified by a ringtone or vibration, and an icon \bowtie will appear on Status bar.

Touch and drag down the Status bar to display the Notification panel, touch the new email to view it. Or you can also access the Gmail Inbox label and touch the new mail to read it.

If you want to go back to the Inbox label while reading a new message, you can press **Back** key or press **Menu** key and touch **Go to inbox**.

You can search for an email by sender, by subject, by label, etc.

- from inbox screen, press Menu key and then touch Search
- enter the keyword you want to search for in the searching box and touch search icon.

To reply or forward emails

When viewing an email, touch \checkmark to expand hidden icons that offer further options.

 Reply/ Reply all
 Touch to enter text-inputting mode, enter the message you want to reply, then touch Send to send this message to one single recipient or all people in a mail loop.

Forward

Touch to forward the message to another person. You are required to enter the new recipient's email address and then touch **Send**.

Managing Gmails by Label

To conveniently manage conversations and messages, you can organize them using a Label.

To label a conversation when reading a conversation's messages, press **Menu** key and touch **Change Labels** and select the label to assign to the conversation.

To view conversations by label when viewing your inbox or another conversation list, press **Menu** key and touch **Go to labels**. Touch a label to view a list of conversations with that label.

Touch and hold an email to produce the following options:

• Read	To view the email message.	
• Archive	To archive the email message.	
• Mute	To mute the entire conversation. When muted, new mails related to this conversation will not be displayed in Inbox , but archived.	
 Mark read/Mark unread 	To mark an email message as read or unread.	
• Delete	To delete the email message.	
• Add star/Remove star	To assign a star or remove the star from the conversation. You can also touch the icon 📩 to add a star or remove the star in inbox screen and email viewing screen.	
• Report spam	To report the email message/conversation as spam.	
Change labels	To add or change the label of the email message or conversation.	
	Touch to learn more	

Help Touch to learn more.

Gmail settings

To manage Gmail settings, press **Menu** key in Inbox screen and touch **More\Settings**.

General preferences

- Message Actions Select to activate an action.
- Clear search Touch to remove the search history.
- Clear "Show Touch to restore default for all senders. pictures"

Touch your Gmail account to manage the account settings.

General settings

Reply all

- Signature To add a signature text to the end of each mail you send.
- **Confirm actions** Select to activate a query when deleting a message or conversation, for double confirmation.
 - Mark the check box to reply to all people in a mail loop by default.
- Auto-advance Touch to select a screen after deleting or archiving a conversation.
- Message text size Touch to select text font.
- Batch operations Select to add conversation to a batch for further operation, like archive, delete, change label, etc.
- Sync inboxes and S labels
- Select to set synchronization frequency.

Notification settings

- Email Select to activate notification when a new email notifications arrives.
- Labels to notify Touch to set notification preferences for synced labels.

4.2.2 Email

Besides your Gmail account, you can also set-up external POP3 or IMAP email accounts in your phone.

To access this function, touch if from Home screen, then select Email.

An email wizard will guide you through the steps to set-up an email account.

- Select an account.
- Enter the email address and password of the account you want to set-up.
- Touch Next. If the account you entered is not provided by your service provider in the phone, you will be prompted to go to the email account settings screen to enter settings manually. Or you can touch Manual setup to directly enter the incoming and outgoing settings for the email account you are setting up.
- · Enter the account name and display name in outgoing emails.
- Touch Done.
- To add another email account, you can press **Menu** key and touch **Accounts** to access Email account screen. Press **Menu** key and touch **Add account** to create.

To create and send emails

- Press Menu key from Inbox screen, and touch Compose.
- Enter recipient(s)'s email address in **To** field, and if necessary, press **Menu** key and touch **Add Cc/Bcc** to include a copy or a blind copy to the message.
- Enter the subject and content of the message.
- Press Menu key, touch Add attachment to send an attachment to the receiver.
- Finally, touch Send.
- If you do not want to send the mail right away, you can touch Save as draft or press Back key to save a copy.

4.3 Google Talk.....



Google's instant messaging service, Google Talk, lets you communicate with your friends whenever they are connected to this service.

To access this feature and sign in, touch **Talk**. All friends added by using Google Talk from the web or phone will be displayed in your friends list.

Touch your own name at the top of your Friends list to set your online status, post a status message, etc. Touch 🔵 to set your online status.



To sign out, press \mathbf{Menu} key from Friends list to display options, touch $\mathbf{Sign}\ \mathbf{out}.$

4.3.1 Chatting with your friends

To start a chat, touch the name of a friend in your Friends list, then enter your message and finally touch **Send**.

You can invite other friends to join in a group chat by pressing **Menu** key, touching **Add to chat** and then select the friend you want to add.

When chatting with more than one friend, you can switch screens by pressing **Menu** key, then touching **Switch chats**.

To return to Friends list screen, press $\ensuremath{\textbf{Menu}}$ key, then touch $\ensuremath{\textbf{Friends}}$ list.

4.3.2 To add a new friend

From Friends list, press **Menu** key to open options list and touch **Add Friend** to add a new friend. Enter the Google Talk ID or Gmail address of the friend you want to add, and then touch **Send invitation**.

A notification with this invitation will be received by the friend. By touching the invitation, the friend can select **Accept** or **Cancel** in response.

You can also check all invitations you have sent or received by pressing **Menu** key from Friends list and touching **More\Invites**.

4.3.3 To close a chat

When you want to end a chat, the following two ways are available:

- From Friends list screen, touch and hold the friend you want to stop chatting with to open Option menu, touch **End chat**.
- Press Menu key from chatting screen directly, and then touch End chat.

4.3.4 To manage your friends

Besides adding new friends to your friends list, the following actions are available for your choice:

- To view all friends/ By default, only friends that you frequently most popular friends
 friends
 To view all friends, press Menu key, then touch All friends. To return to displaying most popular friends screen, press Menu key again, then touch Most popular.
- To make a friend popular
 To ensure a friend is always displayed in your Most popular list, touch and hold the friend's name until the options menu pops up, then touch Always show friend. To remove a friend from Always show friend, touch and hold the friend, and touch Auto show friend.
- To block a friend To block a friend from exchanging messages and remove them from your friends list, touch and hold the friend, then touch **Block friend**. All blocked friends can be viewed by pressing **Menu** key and touching **More\Blocked**. To unblock a friend, touch the name of this friend and touch **OK** when prompted.

4.3.5 Settings

A series of settings are available for your selection by pressing **Menu** key from Friends list screen, and touch **Settings**.

- Mobile indicator Select to display an indicator icon along with your name in other people's Friends list.
- Automatically Select to sign in to your Google Talk account automatically every time you turn on your phone.
- Automatic away Select to set status as Away when the screen is status turned off.
- Clear search Touch to clear previous chat searches history from showing up in the Search box.
- Invitation Select to activate the status bar's notification notifications function when receiving friend invitations.
- IM notifications Select to activate the notification function when a new text chat or invitation to a video/voice chat arrives.
- Select ringtone Select to set a notification ringtone.
- Vibrate Select to activate a vibration alert for this service.
- Terms and privacy Touch to read terms of use and privacy statement.

5 Google Calendar & Clock & Calculator & News & Weather.....


Use Google Calendar to keep track of important meetings, appointments, etc.

To access this function, touch **m** from Home screen, then touch **Calendar**.

5.1.1 Multimode view

You can display the Calendar in daily, weekly, monthly, or agenda view.

To change your Calendar view, press **Menu** key, then touch **Day**, **Week**, **Month** or **Agenda**.



5.1.2 To create new events

You can add new events from any Calendar view.

- Press **Menu** key from Calendar screen, and touch **More\New event** to access new event edit screen.
- Fill in all required information for this new event. If it is a whole-day event, you can select **All day**.
- Invite guests to the event. Enter the email addresses of the guests you want to invite with commas to separate. If the guests use Google Calendar, they will receive an invitation from Calendar and email.
- When finished, touch **Done** from the end of the screen.

To quickly create an event from Day,Week or Month view screen, touch and hold an empty spot or an event to open Option menu, then touch **New event** to enter the event details screen of the time you have previously selected.

5.1.3 To delete or edit event

To delete or edit an event, touch the event to enter details screen, press **Menu** key, touch **Edit event**, or **Delete event**.

5.1.4 Event reminder

If a reminder is set for an event, the upcoming event icon 1 appears on Status bar as a notification when the reminder time arrives.

Touch and drag down the status bar to open notification panel, touch event name to view Calendar notification list.

Touch **Snooze all** to turn off all event reminders for 5 minutes.

Touch **Dismiss all** to delete all reminders from the list.

 $\ensuremath{\text{Press}}$ $\ensuremath{\textbf{Back}}$ key to keep the reminders pending in the status bar and notification panel.

Important options by pressing Menu key from Calendar main screen:

	New event	To add a new event
More	My calenders	Touch to show or hide the calendars
riore	Settings	To set a series of Calendar settings
	Sync calendar	To sync or not sync the calendars

Your mobile phone has a built-in clock.

To access this function, touch **H** from Home screen, then touch **Clock**.

Touch \bigodot icon at the bottom of the screen. Touch Add alarm to set the alarm. Touch Set to save.



5.2.1 To set an alarm

From Clock screen, touch a currently existing alarm or press **Menu** key and touch **Add alarm** to enter the alarm editing screen.

- Enable alarm Select to enable alarm.
 Time Touch to set time
- **Repeat** Touch to select days you want alarm to sound
- **Ringtone** Touch to select a ringtone for the alarm
- Vibrate Select to activate vibration
- Label Touch to set a name for the alarm

When finished, touch **Done** to confirm.

5.2.2 To adjust alarm settings

Press **Menu** key from **Alarms** screen, then touch **Settings**. The following options can now be adjusted:

- Alarm in silent mode
 Alarm volume
 Alarm volume
 Touch to set volume of alarms
- Snooze duration Touch to set temporary turn off time of an alarm
- Side button behavior behavio

5.3 Calculator.....



With Calculator, you can solve many mathematical problems.

To access this function, touch \blacksquare from Home screen, then touch **Calculator**.

There are two panels available: Basic panel and Advanced panel.

To switch between panels, select one of the following two ways:

- Touch and drag the basic screen to the left to open the Advanced panel.
- Or press Menu key from basic panel to open option menu and touch Advanced panel.



Enter a number and the arithmetic operation to be performed, and enter the second number, then touch "=" to display the result. Touch ⁽²⁾ to delete digits one by one, touch and hold ⁽²⁾ to delete all at one time.

When some number or operations have been entered, touch and hold the entering bar to open a menu offering these further operations: $^{(1)}$

- Select all To select all entered text
- Select text To select what you want to select from entered text
- Cut
 To delete selected text
- Copy
 To copy selected text
- Input method To select your preferred input method
- Paste ⁽¹⁾ To paste what you have previously copied to the entering bar

⁽¹⁾ Option will not appear unless copy or cut operation has been made.

5.4 News & Weather.....



Use News & Weather to check the weather and top news stories.

To access this function, touch **mathefactorial** from Home screen, then touch **News & Weather**.

5.4.1 To get details about weather and the news

Touch **Weather** tab to get a one week forecast for the city you set. Touch **()** for a more detailed forecast.

Slide left or right across the screen to view top stories by category. It allows customization showing/hiding various news categories and even creating your own.

To get the latest information while viewing the weather or new headlines, press **Menu** key and touch **Refresh**.

5.4.2 To adjust settings

Press **Menu** key from News & Weather screen, then touch **Settings**. The following options can now be adjusted:

Weather settings

- Use my Check to set location by using the phone's location location service.
- Set location Touch to set location by entering a city or postal code.
- Use metric Check to use metric instead of imperial units.

News settings

- Select news topics
 Check the boxes of news categories which most interest you to include them in the scrolling list of News & Weather tabs. You can also add your own topic by touching Custom topic.
- Prefetch articles Check to download news articles for faster access.
- Prefetch images Check to download news images for faster access.
- News terms of Opens a screen with details about the terms of service service for Google News.
- Mobile privacy Opens a screen with details about Google Mobile privacy policy.

Refresh settings

- Auto-refresh Check to update News & Weather information automatically, at the frequency you set with **Refresh** interval.
- **Refresh interval** Touch to set how often news and weather automatically update.
- **Refresh status** Displays the date and time of the last refresh of news and weather.

6 Getting connected.....

To connect to the internet with this phone, you can use GPRS/EDGE/3G networks or Wi-Fi, whichever is most convenient.

6. Connecting to the Internet

6.1.1 GPRS/EDGE/3G

The first time you turn on your phone with SIM card inserted, it will automatically configure network service: GPRS, EDGE or 3G.

To check the network connection you are using, press **Menu** key on Home screen, then touch **Settings\Wireless & networks\Mobile networks\ Network operators** or **Access Point Names**.

To create a new access point

A new GPRS/EDGE/3G network connection can be added to your phone with the following steps:

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Mobile networks\Access point names.
- For dual SIM model, select the SIM name in the screen that opens.
- Then press Menu key again and the touch New APN.
- · Enter the required APN information.
- When finished, press Menu key and touch Save.

To activate/deactivate Data roaming

When roaming, you can decide to connect/disconnect to a data service.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Mobile networks\ Data roaming. For dual SIM model, please touch Settings\SIM management\Roaming\Data roaming.
- Mark/Unmark the SIM card checkbox to activate or deactivate data roaming.
- When Data roaming is deactivated, you can still perform data exchange with a Wi-Fi connection (refer to section 6.1.2 Wi-Fi).

To limit your data connection to 2G networks only

To save battery and extend battery life, you can set to activate 2G networks (GPRS or EDGE) only.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Mobile networks\Network mode.
- Touch **2G only** in the dailog that opens.

6.1.2 Wi-Fi

Using Wi-Fi, you can connect to the Internet when your phone is within range of a wireless network. Wi-Fi can be used on phone even without a SIM card inserted.

To turn Wi-Fi on and connect to a wireless network

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Wi-Fi.
- Mark/Unmark the checkbox to turn on/off Wi-Fi.
- Touch **Wi-Fi settings**. The detailed information of detected Wi-Fi networks is displayed in the Wi-Fi networks section.
- Touch a Wi-Fi network to connect. If the network you selected is secured, you are required to enter a password or other credentials (you may contact network operator for details). When finished, touch Connect.

To activate notification when a new network is detected

When Wi-Fi is on and network notification is activated, the Wi-Fi icon will appear on the status bar whenever the phone detects an available wireless network within range. The following steps activate the notification function:

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Wi-Fi settings\Network notification.
- Mark/Unmark the checkbox to activate/deactivate this function.

To add a Wi-Fi network

When Wi-Fi is on, you may add new Wi-Fi networks according to your preference.

• Press Menu key from Home screen.

- Touch Settings\Wireless & networks\Wi-Fi settings\Add Wi-Fi network.
- · Enter the name of the network and any required network information.
- Touch Save.

When successfully connected, you phone will be connected automatically the next time you are within range of this network.

To forget a Wi-Fi network

The following steps prevent automatic connection to networks which you no longer wish to use.

- Turn on Wi-Fi, if it's not already on.
- In the Wi-Fi settings screen, touch and hold the name of the network.
- Touch Forget network in the dialog that opens.

To add a WPS network

WPS (Wi-Fi Protected Setup) is an easy way for users to access Wi-Fi network.

- Press Menu key from Home screen.
- Touch Settings\Wireless&networks\Wi-Fi settings\WPS connect to get access to a WPS network.

To enable proxy

When Wi-Fi is on, you may set up a proxy to make indirect network connections to other network services.

- Touch Settings\Wireless & networks\Wi-Fi settings\Enable proxy.
- Touch **Proxy settings** to enter host and port.
- Touch OK.

6.2 Bro

Browser.....



Using Browser, you can enjoy surfing the Web.

To access this function, touch **m** from Home screen, then touch **Browser.**

To go to a web page

On Browser screen, touch the URL box at the top, enter the address of the web page, then touch \Rightarrow . Some web sites scroll the URL box off the top of the screen, but you can slide the page down to bring it into view.

To set home page

- Press Menu key from Browser screen to display option menu, touch More\Settings\Set home page.
- Enter the URL of the website you want to set as your home page.
- Finally touch **OK** to confirm.

6.2.1 Viewing web pages

When opening a website, you can navigate on web pages by sliding your finger on the screen in any direction to locate the information you want to view.

To zoom in/out of a web page

Zoom controls will be activated when scrolling the screen using your finger. Touch the plus or minus to the side of the Zoom control to zoom in or out.

To quickly zoom into a section of a web page, double-tap on the section you want to view. To return to normal zoom level, double-tap again. You can also pinch current web pages.

To find text on a web page

- Press Menu key from web page screen, then touch More\Find on page.
- Enter the text or phrase you want to find.
- The first word with matching characters will be highlighted on the screen, and subsequent matches are boxed.
- Touch the left or right arrow to switch to the previous or next matching items.
- When finished, you can touch 🐹 to close the search bar.

To copy text on a web page

You can copy text from a web page and paste it into emails or $\ensuremath{\mathsf{SMS}}\xspace/\ensuremath{\mathsf{MMS}}\xspace$ messages.

- Press Menu key from web page screen, then touch More\Select text.
- Place your finger at the start of the text you want to copy and then drag it to the end of the text.
- Raise your finger. Selected text is highlighted in color. Touch the selected text to copy.

To paste the copied text into an email or SMS/MMS message, touch and hold the enter box and then touch ${\bf Paste}$ on the options menu.

To open new window/switch between windows

Multiple windows can be opened at the same time for your convenience.

- To view all currently open windows, press **Menu** key then touch **Windows**.
- Touch **New window** to open a new window.
- Touch a window you want to view.

To close a window, touch \mathbf{X} on the window you want to close.

Other options:

- Close To close all tabs or minimize the web page. (press Menu key on web page screen, then touch Close).
- Page info
 To view more information about the current page (press Menu key on web page screen, then touch More\Page info).
- Forward To forward the pages you have opened (press Menu key on web page screen, then touch Forward).
- **Backward** To review the pages you have opened (press **Menu** key on web page screen, then touch **Backward**).
- Share page To share the current page with your friends via various ways, like Message, Email, Bluetooth, etc. (press Menu key on web page screen, then touch More\Share page).

6.2.2 Manage links, history

To manage a link, phone number or address displayed on a web page

- Link Touch the link to open the web page. Touch and hold the link to open options for further operation, like open in new window, save link, share link, copy link, etc.
 Phone number Touch to call the phone number.
- Address
 Touch to open Google Maps and locate the address

To view Browser history

- Press Menu key from Browser screen
- Touch More\History tab to view browser history.

To view your most frequently visited pages

- Press Menu key from Browser screen
- Touch More\History
- Touch Most visited tab to view your most frequently visited pages.

6.2.3 Manage downloads

To access Downloads

Downloads gives you easy access to any file downloaded from the browser, email or another application, and you can manage and store your download more conveniently.

Enter this menu by either:

• Touching from Home screen and selecting **Downloads**.

Or:

• Touching from Home screen and selecting Browser. Then press Menu key and touch More\Downloads.

To download a web application/view your downloads

Before downloading a web application, you need to enable your phone to download web applications (press **Menu** key from Home screen, touch **Settings\Applications**, mark check box of **Unknown sources**, finally touch **OK** to confirm).

To download a file, touch and hold the item you want to download, then touch \mathbf{Save} on the menu that opens.

To cancel a download, press **Menu** key and touch **More\Downloads**, then select items you want to cancel downloading and finally touch **Cancel**.

To view items you have downloaded, press **Menu** key and touch **More Downloads**. You can delete the downloaded items by selecting the items and touching **Delete**.

6.2.4 Manage bookmarks

To bookmark a web page

- Open the web page you want to bookmark.
- Press Menu key and touch Bookmarks.
- Touch Add bookmark
- \bullet Enter the name, location and folder if needed and touch \mathbf{OK} to confirm.

To open a bookmark

- Press Menu key and touch Bookmarks.
- On the **Bookmarks** tab, touch the bookmark you want to open.
- You can also touch and hold to display the options screen, then touch **Open** or **Open in new window**.

To edit a bookmark

- Press Menu key and touch Bookmarks.
- On the **Bookmarks** tab, touch and hold the bookmark you want to edit.
- Touch Edit bookmark.
- Enter your changes.
- When finished, touch **OK** to confirm.

Touch and hold a bookmark in the bookmark list to view these additional options:

- Share link To share the bookmark.
- Copy link URL To copy the bookmark link.
- Add shortcut to To add a bookmark shortcut to the Home Screen.
- **Delete bookmark** To delete a bookmark.
- Set as homepage To set the bookmark link as homepage.

6.2.5 Settings

A series of settings are available for your adjustment. To access Browser settings, press Menu key from Browser screen, and touch More\ Settings.

Page content settings

- Text size Touch to select the size of the text display: Tiny, Small, Normal, Large, or Huge.
- **Default zoom** Touch to select the magnification level by default.
- Open pages Mark the checkbox to open web pages zoomed in overview out, in an overview.
- Text encoding Touch to select the character-encoding standard.
- Block pop-up Mark the checkbox to prevent pop-up windows. windows
- Load images Mark to display images on web pages.
- Auto-fit pages Mark to format web pages to fit the screen.

Mark to display pages only in landscape screen

- Landscape only display
- Enable JavaScript Mark to enable JavaScript.

orientation.

- Enable plug-ins Mark to enable plug-ins.
- Open in Mark to open new windows behind the current background one.
- Set home page Touch to set home page.

Privacy settings

- Clear cache Touch to clear locally cached content and databases.
- Clear history Touch to clear the browser history.
- Accept cookies Mark to allow sites to save and read cookie data.
- Clear all cookie Touch to clear all browser cookies. data
- Remember form Mark to remember data in forms for later use. data
- Clear form data Touch to clear all the saved form data.
- Enable location Mark to allow sites to request access to your location.
- Clear location Touch to clear location access for all websites. access

Security settings

- Remember Mark to remember username and passwords for websites.
- Clear passwords Touch to clear all saved passwords.
- Show security Mark to show warning if there is a problem with warnings a site's security.

Advanced settings

- Set search engine Touch to select a web search engine, which will be used when you enter search terms in the URL box.
- Website settings Touch to view advanced settings for individual websites.
- Reset to default Touch to clear all browser data and reset all settings to default.

6.3 Connecting to Bluetooth devices (1)

Bluetooth is a short-range wireless communications technology that you can use to exchange data, or connect to other Bluetooth devices for various uses.

To access this feature, press Menu key from Home screen, touch Settings\ Wireless & Networks\Bluetooth or Bluetooth settings.

To turn on Bluetooth

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Bluetooth or Bluetooth settings.
- Mark/Unmark the checkbox to activate/deactivate this function.

(I) You are recommended to use ALCATEL ONE TOUCH Bluetooth headsets, which have been tested and proved compatible with phone. You can go to www. alcatelonetouch.com for more information about ALCATEL ONE TOUCH Bluetooth headset.

To change device name

To make your phone more recognizable, you can change your phone name which is visible to others.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Bluetooth settings\Device name.
- Enter a name, and touch OK.

To make device visible

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Bluetooth settings\Discoverable.
- · Mark/Unmark the checkbox to activate/deactivate this function.

To pair/connect your phone with a Bluetooth device

To exchange data with another device, you need to turn Bluetooth on and pair your phone with the Bluetooth device with which you want to exchange data.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Bluetooth settings
- Touch Scan for devices
- · Select a Bluetooth device you want to be paired with in the list.
- Read Bluetooth pairing request, and then touch Pair.
- If the pairing is successful, your phone connects to the device.

To disconnect/unpair from a Bluetooth device

- Touch and hold the device name in the Bluetooth settings screen.
- · Touch Unpair or Disconnect & Unpair in the menu that opens.

6.4 Connecting to a computer via USB

With the USB cable, you can transfer media files and other files between your phone's microSD card and the computer.

To connect/disconnect your phone to/from the computer

To connect your phone to the computer:

- Use the USB cable that came with your phone to connect the phone to a USB port on your computer. You will receive a notification that the USB is connected.
- Open the Notifications panel and touch USB connected.
- Touch **Mount** and then **OK** in the dialog that opens to confirm that you want to transfer files.

To disconnect:

- Unmount the microSD card on your computer.
- Open the Notifications panel and touch Turn off USB storage.
- Touch Turn Off in the dialog that opens.

To safely remove the microSD card from your phone

The microSD card can be removed from your phone any time the phone is powered off.

- Press Menu key from Home screen.
- Touch Settings\SD card & phone storage.
- Touch Unmount SD card.

You can now safely remove the microSD card from the phone.

To format a microSD card

- Press Menu key from Home screen.
- Touch Settings\SD card & phone storage.
- Touch **Unmount SD card**. You can format a microSD card only when it is unmounted.
- Touch **Format SD card**. On the screen that warns you that formatting the microSD card will erase its contents, touch Format SD card .

6.5 Sharing your phone's mobile data connection

You can share your phone's mobile data connection with a single computer via a USB cable (USB tethering) or with up to eight devices at once by turning your phone into a portable Wi-Fi hotspot.



The functions below may incur additional network charges from your network operator. Extra fees may also be charged in roaming areas.

To share your phone's data connection via USB

Use the USB cable that along with your phone to connect the phone to a USB port on your computer.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Tethering & portable hotspot.
- Mark\unmark the check box of **USB tethering** to activate/deactivate this function.

To share your phone's data connection as a portable Wi-Fi hotspot

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Tethering & portable hotspot.
- Mark\unmark the check box of **Portable Wi-Fi hotspot** to activate/ deactivate this function.

To rename or secure your portable hotspot

When Portable Wi-Fi hotspot is activated, you could change the name of your phone's Wi-Fi network (SSID) and secure its Wi-Fi network.

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\Tethering & portable hotspot\Portable Wi-Fi hotspot settings.
- Touch Configure Wi-Fi hotspot to change the network SSID or set your network security.
- Touch Save.

6.6 Connecting to virtual private networks

Virtual private networks (VPNs) allow you to connect to the resources inside a secured local network, from outside that network. VPNs are commonly deployed by corporations, schools, and other institutions so that their users can access local network resources when not on campus, or when connected to a wireless network.

To add a VPN

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\VPN settings\Add VPN.
- Touch the type of VPN to add.
- In the screen that opens, follow the instructions from your network administrator to configure each component of the VPN settings.
- Press Menu key and touch Save.

The VPN is added to the list on the VPN settings screen.

To connect/disconnect to a VPN

To connect to a VPN:

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\VPN settings.
- \bullet VPNs you have added are listed; touch the VPN you want to connect with.
- In the dialog that opens, enter any requested credentials and touch Connect.

To disconnect:

• Open the Notifications panel and touch the resulting notification for the VPN connection.

To edit/delete a VPN

To edit a VPN:

- Press Menu key from Home screen.
- Touch Settings\Wireless & networks\VPN settings.
- VPNs you have added are listed; touch and hold the VPN you want to edit.
- Touch Edit network.
- After finishing, press Menu key and touch Save.

To delete:

- Touch and hold the VPN you want to delete, in the dialog that opens, touch **Delete network**.
- Touch OK to confirm.

7 Multimedia applications

7. **C**amera

•

Your mobile phone is fitted with a Camera and Camcorder for taking photos and shooting videos.

Before using Camera or Camcorder, please ensure that a microSD card where all pictures and videos are stored is correctly installed. Also, be sure to tear off the protective lens film before use to avoid it affecting your picture quality.

To access this function, touch **the mean of the second the second**

Touch once on screen, six icons will appear enable you to do settings.



Touch to view pictures or play video you have taken.

Drag up or down to switch between Camera mode and Video mode.

Touch to take a picture or record a video.

To take a picture

The screen acts as the viewfinder. First position the object or landscape in the viewfinder, and touch 0 icon to take the picture, which will be automatically saved.

Zoom in/zoom out

Touch icon to open the Zoom control and slide the scroll bar to zoom in or out gradually. Touch the screen twice to zoom all the way in or out.

To shoot a video

Switch Camera mode to Video mode or access Camcorder directly from the applications list. First position the object or landscape in the viewfinder, and touch () icon to start recording. Touch () icon to stop shooting. The video will be automatically saved.

7.1.1 Settings in framing mode

Before taking a photo/shooting a video, you can adjust a number of settings in framing mode.

Camera settings:

- Settings Touch to enter a scrolling list of settings: EV, Scene mode, Color effect, etc.
- Advanced Choose to set several options such as Bursts shot, settings Timer, Anti Banding, etc.
- Location Touch to turn on/off stored location information of pictures by using the phone's GPS.
- White balance Touch to adjust color in different lights: Auto, Incandescent, Daylight, Fluorescent, Cloudy, etc.
- Zoom Touch to open the Zoom control and slide the scroll bar to zoom in or out gradually.

Video/Camcorder settings:

 Settings 	Touch to enter a scrolling list of settings: EV, Scene	
	mode, Color effect, etc.	
Advanced settings	Microphone	Touch to turn on/off the microphone when shooting a video.
	Anti Banding	Touch to set frequency (50Hz or 60Hz).
• White balance	Touch to adjust color in different lights: Auto, Incandescent, Daylight, Fluorescent, Cloudy, etc.	
Zoom	Touch to one	n the Zoom control and slide the

• Zoom Touch to open the Zoom control and slide the scroll bar to zoom in or out gradually.

Press Menu key in framing mode, the following options are available:


Gallery	Touch to access Gallery.
Switch to camera/ video	Touch to switch between camera and video.

7.2 Gallery

Gallery acts as a media player for you to view photos and playback videos.

To access this function, touch \blacksquare from Home screen, then touch Gallery.

From this menu, you can access Camera for taking a picture or video.



To view a picture/play a video

Pictures and videos are displayed by albums in Gallery.



Touch and scroll the bar to switch. This will change the album view from grid to stack.



- Touch the picture/video directly to view or play it.
- You can also view previous or next pictures/videos by sliding left or right.

Working with pictures

You can work with pictures by rotating or cropping them, sharing them with friends, setting them as contact ID or wallpaper, etc.

Locate the picture you want to work on, press **Menu** key from full-screen picture view.



To crop a picture, touch a picture to view controls, press **Menu** key and touch **More\Crop**. The cropping square appears in the middle of the picture. Select the portion to crop, touch **Save**.

Batch operation

Gallery provides multi-select function, so that you can work with pictures/ videos in batches.

Open the main Gallery window, press **Menu** twice, and mark the checkbox before the file you want to work on, then perform further actions, like delete, share, etc.

7.3 You

You Tube

YouTube is an online video-sharing service where the user can download, share and view videos. It supports a streaming function that allows you to start watching videos almost as soon as they begin downloading from the Internet.

To access this function, touch **Here** from Home screen, then touch **YouTube**.



As an online video service, your phone must have a network connection to access $\ensuremath{\mathsf{YouTube}}$.



By pressing **Menu** key from YouTube screen, you can rate, share, label as favourite, etc. For details about these features, please visit the YouTube website: www.YouTube.com

7.3.1 Watch videos

Touch a video to play it.

Touch video playing screen to display playback controls with which you can pause, skip forward or backward, or drag the progress bar to the point you want to watch.

To exit video playing screen, press **Back** key to return to video list.

7.4 Music

Using this menu, you can play music files stored on the microSD card in your phone. Music files can be downloaded from computer to microSD card using a USB cable.

To access this function, touch **Music**.

You will find four libraries in which all songs are classified: **Artists**, **Albums**, **Songs**, and **Playlists**. Touch a category and view the list.

To delete a song, press **Menu** key from playback screen and then touch **Delete** to remove it from the microSD card.

You can also set a song as a ringtone, press **Menu** key from playback screen to display option menu, then touch **Use as ringtone**.

7.4.1 Playing music

From any of the four library screens, touch a song to play it back.



- Touch to play the current playlist in shuffle mode (tracks are played in random order).
- O Touch to open the current playlist.
- Touch to toggle repeat mode: Don't repeat, Repeat the playlist, or Repeat the current track.
- **O** Touch to skip to the next track in the album, playlist, or shuffle.
- Touch to pause/resume playback.
- **o** Touch to skip to the previous track in the album, playlist, or shuffle.
- Touch to view lyrics

Adjust volume

To adjust the volume, you can press Volume up/down key.

7.4.2 Using Party shuffle

All songs will be displayed in order by default. When Party shuffle is activated, some songs will be selected and played at random. Press **Menu** key, then touch **Party shuffle** to turn on this function. To turn it off, press **Menu** key again, then touch **Party shuffle off**.

7.4.3 Using Sound effects

When Sound effects is activated, songs will be played using various different filters preset by you. Press **Menu** key, then touch **Sound effects** to enter settings screen. Mark **Enable sound effects** to turn on this function. Touch sound effect name to set, and mark it to activate.

7.4.4 Working with playlists

Playlists allow you to conveniently organize all the songs stored in the card.

You can create a new playlist, add a song to the list, rearrange the order of the list, and delete or rename a playlist.

To create a playlist

Press **Menu** key from playback screen to display the option menu, touch **Add to playlist**, then touch **New**, enter the name and finally touch **Save**.

To change the order of songs in a playlist

Enter a playlist, drag a song up or down to change the order within the playlist.

To delete a song

Locate the song you want to delete, touch and hold or press **Menu** key from playback screen to display option menu, then touch **Delete**.

To delete a playlist

Locate the playlist you want to rename, touch and hold to display option menu, then touch **Delete**. When finished, touch **Save**.

8 Google Maps.....

8.1 Get My Location

8.1.1 Choose a data source to decide My Location

Press Menu key from Home screen, touch Settings\Location.

- Mark the check box of Use wireless networks to set Wi-Fi and/or mobile networks as My Location data source.
- Or mark the check box of **Use GPS satellites** to set GPS as My Location data source. You can also mark **GPS EPO** assistance or **A-GPS** to speed up the GPS location fix time.

8.1.2 Open Google Maps and view My Location

Touch from Home screen, then touch Maps.

Touch O in search bar to identify your location.

The map will then center on a blue arrow with a blue circle around. Your actual position is within the blue circle.



To move the map, drag the map with your finger.

To zoom in and out of a map, touch the plus or minus side of the zoom control $\stackrel{+}{=}$, or you can also zoom in/out by double-tapping a location on screen.

To clear the map history, press Menu key and touch Clear Map.

8.2 Search for a location

- While viewing a map, press **Menu** key and touch **Search**, or you can directly press **Search** key on keyboard to activate search function.
- In the search box, enter an address, a city or a local business.
- Touch the search icon and in a while your search results will appear on the map highlighted by markers with letter labels.



You can touch a marker to open a balloon that contains a label. Touch the balloon to open a screen with more handy information about the location.

8.3 Star a location

Just like bookmarking a web address on the Internet, you can star any position on the map for later use.

8.3.1 How to star (or unstar) a location

- Touch and hold a location on a map
- Touch the address rectangle that opens
- Touch the gray star at the top of the screen to star the location. (Or touch a gold star to unstar that location.)



8.4 Get driving, public transport or walking directions

8.4.1 Get suggested routes for your trip

• Press Menu key from maps screen and touch Directions.

	۱ 🗧	-	18:09
My Location			Ľ
End point:			맵
		Ŕ	
	Get	direction	5

- Touch enter bar or **[1]** to edit your start point by one of the following methods: entering an address, using My Location, selecting a start point on a map, selecting a starred item, selecting an address from your contacts or using search history.
- Do likewise for your end point.
- To reverse directions, press Menu key and touch Reverse Start & End.
- Then select a transport mode: driving by car, using public transport, or walking directions.
- Finally touch Get directions.
- A couple of suggested routes will appear in a list. Touch any routes to view their respective detailed directions.

To get reverse directions for a route you've already made, simply open that route's directions window and select **Reverse**. No need to enter your start point and end point again.

8.4.2 Preview suggested routes and decide on a route more preferable or feasible to you

You can preview each turn in your route in Navigation, Satellite, and other views.

- Touch a left or right arrow to preview the next or previous leg of your route.
- You can view turn-by-turn directions in a list by touching 👼 , press **Back** key to return to previous view.

When selecting a more preferable or feasible route, distance and time will be the two most important factors for your evaluation. Distance and estimated time will be displayed at the top of the directions screen.

8.4.3 Search for locations along your route

Please refer to section 8.2 for detailed information.

8.4.4 View route progress and calculate estimated arrival time

To view your route progress, pinpoint My Location, zoom out until the whole route goes into one screen, with both finished and unfinished miles in sight.

Start another Directions screen based on your current and intended destination locations. Estimated arrival time will be shown in the results. Please note that the estimated arrival time is not available for the public transport mode.

8.4.5 View traffic conditions on your route

At the lower-left corner of navigation view, a traffic light indicates the overall traffic conditions on your route, next to the estimated time of arrival at your destination. You can also view the traffic conditions on each segment of your route.

Touch the traffic light at the lower left of the Navigation View. Your route opens in Traffic View, with color coding to indicate the traffic along the way. Touch the navigation icon to return to your current location in Navigation View

8.4.6 Get an alternative route to your destination

If traffic is slow on your current route, or if you just want to try a different route, you can request an alternative route from Google Maps with turnby-turn Navigation service.

Press **Menu** key and touch **Route information**. Touch the alternative route icon. An alternative route is drawn on the map.

8.5 Arrangement of Layers

Layers allow you to view locations and additional information overlaid on the map. You can add multiple layers or remove only certain layers so you control exactly what information you want visible on the map at one time.

8.5.1 To view multiple layers

- Touch sin the search bar
- All available layers are listed (like Traffic, Satellite, Latitude, etc), select one to view.

8.5.2 To open Street View for a location

- Touch and hold a location to display a balloon with the address and a Street View thumbnail.
- Touch the balloon and touch **Street view**.

8.5.3 To clear the map

After you get directions or search on a map, you can clear the markers/ layers that have been drawn: press **Menu** key on maps screen and touch **Clear Map**.

8.6 Join Latitude to see your friends' locations and share yours with them

With Google Latitude, you can:

- see your friends' locations on a map or in a list.
- quickly contact your friends with a text message, instant message, or phone call.
- you can share, set, hide your location, or sign out of Google Latitude.
- · control who sees your location, and at what level of detail.
- add Latitude widget to home screen to see nearby friends at a glance.

8.6.1 How to invite friends to share their locations

- Press Menu key from Latitude screen, touch Add friends.
- Touch Select from Contacts or Add via email address.
- After selecting your chosen contacts touch Add friends at the bottom of the screen.

When finished, an invitation will be sent to the friends you have invited.

To respond to an invitation, you can select one of the following:

- Accept and share You and your friend can share locations with back each other.
- Accept, but hide You can view your friend's location, but they can not view yours.
- Don't accept No locations can be shared between you and your friend.

8.6.2 To view your friends' location

You can view your friends' locations on a map or in a list.

 Map view When Google Maps is opened, your friends' locations will display with their photo icon for identification.

8.6.3 To connect with your friends

Select a contact, you can communicate with your friend and set privacy options.

- Show on map Locate the friend's position on the map.
- Chat using Google Send instant message to the friend.
 Talk
- Send email Send email to the friend.
- **Directions** Get directions to this friend's location.
- Share best Set to share best available location to this friend. available location
- Hide from Set to hide your location from this friend.
- Share only Set to share only locations at city level, but not city level location street level, etc.

• Remove Remove this friend from your list and stop sharing information with him or her.

8.6.4 To control what you share

You can control the information you want to share with your friends.

Touch Latitude and press Menu key, then press Location settings.

The following options are available to choose from:

- Detect your Enable Latitude to detect your location automatically when you move around.
- Set your location Select a location on the map manually.
- Do not update + your location
- e Hide your location from all friends.
- Enable location Location history won't be shared with others. history
- Sign out of Deactivate Latitude and stop sharing. Latitude

9 Others.....

9.1 File Manager.....

To access this function, touch **Here** from Home screen, then touch **File Manager**.

File Manager works with your SD card instead of your phone memory. To use it, you have to install your SD card first. See page 17 for instructions on inserting the SD card.

File Manager displays all data stored on the microSD card, including applications, media files downloaded from Android Market, YouTube or other locations; video, pictures or audios you have captured; other data transferred via Bluetooth, USB cable, etc.

When you download an application from PC to microSD card, you can locate the application on File Manager, then touch it to install it in your phone.

File Manager allows you to perform and be really efficient with the following common operations: create (sub) folder, open folder/file, view, rename, copy, delete, play, share, etc.

To access this function, touch from Home screen, then touch **Notes**.

Use **Notes** to note down inspirations, ideas, excerpts, things to do and all those things you may want to keep for future reference.

Existing notes can be sent via Bluetooth, message or Email.

Sound Recorder allows you to record voice/sound for seconds/hours.


9.4 FM Radio.....

Your phone is equipped with a radio $^{(1)}$ with RDS $^{(2)}$ functionality. You can use the application as a traditional radio with saved channels or with parallel visual information related to the radio program on the display if you tune to stations that offer Visual Radio service.

To access this function, touch **m** from Home screen, then touch **Radio**.



To use it, you must plug in your headset, which works as an antenna connected with your phone.



- (I) The quality of the radio depends on the coverage of the radio station in that particular area.
- ⁽²⁾ Depending on your network operator and market.

Available options:

- Exit Turn off the radio.
- Search Touch to search for all available stations automatically.
- **RDS settings** ⁽¹⁾ Mark the check box to enable the function.

9.5 Battery Saver



To access this function, touch from Home screen, then touch **Battery**

Battery Saver includes an accurate overview of battery usage and provides an efficient way of power saving by utilizing a range of battery settings and by killing non-essential tasks.

9.6 Setup Wizard



To access this function, touch **EV** from Home screen, then touch **Setup Wizard**.

Setup Wizard helps to set up your phone in multiple ways: language, input method, mobile data connection, account setup and synchronization, system update, etc. This will also be performed the first time you power on your phone.

9.7 Office suite

To access this function, touch **m** from Home screen, then touch **OfficeSuite**.

OfficeSuite helps to process documents faster and more accurately. You can open and edit different types of format.

9.8 Traffic Manager



To access this function, touch \blacksquare from Home screen, then touch **Traffic Manager**.

Traffic Manager helps to check the data you have used, including general calls and messages as well as applications, which will avoid extra fees from your network operator.

9.9 Alcatel Help



Alcatel Help provides help when you have questions or need assistance when using the phone.

9.10 Voice Dailer

To access this function, touch **the mean of the second sec**

Voice Dialer helps to place a phone call from a spoken contact name or a phone number.

^(I) Depending on your network operator and market.

9.11 Voice Search.....

To access this function, touch \blacksquare from Home screen, then touch Voice Search.

Voice Search helps to call your contacts, get directions, send messages, and to perform a number of other common tasks, in addition to searching the web.

9.12 Other applications ⁽¹⁾.....

The previous applications in this section are preinstalled to your phone. To read a brief introduction of the preinstalled 3rd party applications, please refer to the leaflet provided with the phone. You can also download more 3rd party applications by going to Android Market on your phone.

0 Settings..... @

To access this function, touch **m** from Home screen, and touch **Settings** on applications list, or you can also press **Menu** key from Home screen and touch **Settings**.

10.1 SIM management ⁽¹⁾

10.1.1 SIM information

Mark the check box of the SIM card to enable this setting. Touch the SIM name on the left to edit details.

Edit SIM name	Touch to enter a SIM name.
Enter phone number	Touch to set the phone number.
Set background color	Touch to set background color for the SIM card.
Display numbers	Touch to select the way numbers display.

10.1.2 Default SIM

Touch to set your preferred default SIM.

Voice call

Set default SIM for placing a voice call.

Video call⁽²⁾

Check default SIM for placing a video call.

⁽¹⁾ Just for dual SIM mode.

⁽²⁾ Depending on your model and network operator.

Messaging

Set default SIM for sending a message.

Data connection

You can either set the data connection via SIM1/SIM2, or select **Off** to prevent your phone from transmitting data on any mobile networks. This is useful to avoid incurring significant data use charges on local carrier mobile networks, particularly if you do not have a mobile data agreement on one of the SIMs.

10.1.3 General settings

Roaming

Data roaming If you don't need to transmit data on other carriers' mobile networks, unmark the check box to avoid incurring significant roaming charges.

Show roaming Set reminder: Once, Always, Never. reminder

10.2 Wireless & networks

10.2.1 Airplane mode

Mark the check box of **Airplane mode** to simultaneously disable all wireless connections including Wi-Fi, Bluetooth and more.

10.2.2 Wi-Fi

Using Wi-Fi you can now surf the Internet without using your SIM card whenever you are in range of a wireless network. The only thing you have to do is to enter the **Wi-Fi settings** screen and configure an access point to connect your phone to the wireless network.

For detailed instructions on using Wi-Fi, please refer to section 6.1.2 Wi-Fi.

10.2.3 Bluetooth

Bluetooth allows your phone to exchange data (videos, images, music and more) over short distances with another Bluetooth supported device (phone, computer, printer, headset, car kit and more).

For more information on Bluetooth, please refer to section **6.3 Connecting** to Bluetooth devices.

10.2.4 Tethering & portable hotspot

This function allows you to share your phone's mobile data connection via USB or as a portable Wi-Fi access point (Please refer to section 6.5).

10.2.5 VPN settings

A mobile virtual private network (mobile VPN or mVPN) provides mobile devices with access to network resources and software applications on their home network, when they connect via other wireless or wired networks. Mobile VPNs are used in environments where workers need to keep application sessions open at all times, throughout the working day, as the user connects via various wireless networks, encounters gaps in coverage, or suspend-and-resumes their devices to preserve battery life. A conventional VPN cannot survive such events because the network tunnel is disrupted, causing applications to disconnect, time out, fail, or even the computing device itself to crash.

For more information of VPN, please refer to section **6.6 Connecting to virtual private networks**.

10.2.6 Mobile networks

Data usage

Touch to view how much data has been transmitted over a mobile network in the current period for a particular SIM card. You can also reset the data usage value.

Network mode

You can select your preferred network with this menu.

Access Point Names

Touch to enter Access Point Names list, where you can check the data connection you are using. You can also add/delete/edit an APN $^{\rm (I)}$. (refer to section 6.1.1 GPRS/EDGE/3G)

Network operators

Touch to select a network operator.

10.2.7 GPRS transfer prefer

You can connect to a GPRS service and GSM service (voice, SMS), but using only one or the other at a given time. Mark the check box of **GPRS transfer prefer** to prevent data transmission during a voice call.

10.3 Call settings

Use Call settings to configure normal phone call settings and other special features offered by your carrier. You can also use Call settings to configure the phone so that it can place outgoing calls only to a fixed set of phone numbers.

10.3.1 Voice call

Voice mail

- Voice mail service Opens a dialog where you can select your carrier's voice mail service or another service.
- Voice mail settings If you are using your carrier's voice mail service, this opens a dialog where you can enter the phone number to use for listening to and managing your voice mail. You can enter a comma (,) to insert a pause into the number — for example, to add a password after the phone number.

Call forwarding

Touch to configure how your calls are forwarded when you are busy, unanswered or unreachable.

Call blocking

Touch to configure Call barring settings. Mark the check box to activate the call barring for outgoing and incoming calls.

Additional settings

- Caller ID Opens a dialog where you can set whether your phone number is displayed when making calls.
- Call waiting Mark the check box to notify you of a new incoming call.

⁽¹⁾ Application availability depends on country and operator.

10.3.2 Other settings

Fixed Dialing Numbers

Fixed Dialing Number (FDN) is a service mode of SIM, where outgoing calls are restricted to a set of phone numbers. These numbers are added to the FDN list. The most common practical application of FDN is for parents to restrict the phone numbers to which their children can dial.

For security reasons, you'll be prompted to enable FDN by entering SIM PIN2 which is usually acquired from your service provider or SIM maker.

Call cost

Touch to view the Last call cost/Total cost/Max cost/Reset call cost/ Currency and unit price, modify or reset them.

Cell broadcast

Enable receipt of CB messages by marking the check box of **Cell broadcast**.

You can access a series of adjustable CB settings by touching **Cell broadcast settings**.

Minute reminder

Mark the check box to enable minute reminder at 50s of every minute during a call.

Phone settings

If you want to reject a call with SMS, you might touch **Phone settings** to edit default message or select to edit massage before sending.

TTY settings

TTY mode can be used by people who are deaf, have bad hearing or speech impairments.

After connecting the cell phone and TTY machine it connects to a relay service, which converts incoming speech to text for the person using the TTY and converts outgoing text from the TTY machine to a spoken voice for the person on the other end of the conversation.

10.4 Audio profiles

Use the Audio profiles settings to configure ringtones for different events and environments.

To revert to the default settings, press Menu key and touch Reset.

10.4.1 General

To modify the sound settings within any profile, touch **General** to view the following functions by scrolling up/down. When finished, mark the check box on the right of the profile's name to activate the action.

- Phone vibrate Mark the check box to vibrate phone for incoming calls.
- Volume Touch to set volume for incoming calls, alarm and notifications.
- Phone ringtone Touch to set your default voice incoming call ringtone.
- Notification Touch to set your default notification ringtone.
- Audible touch Mark the check box to enable playing tones when using dial pad.
- Audible selection Mark the check box to enable playing sound when making screen selection.
- Screen lock sounds Mark the check box to enable sounds to play when locking and unlocking the screen.
- Haptic feedback Mark the check box to activate vibration when pressing soft keys and on certain UI interactions.

10.4.2 Silent

This profile will silence all sounds except media & alarms.

10.4.3 Meeting

When this is selected the phone will not ring or beep by default unless an alarm has been set. A new event will cause it to vibrate.

10.4.4 Outdoor

This profile is designed for outdoor users who require louder ringtones.

10.5 Display

• Brightness	Touch to adjust the brightness of the screen.
• Orientation	Mark the check box to activate automatic orientation switch when rotating phone.
Animation	Touch to select whether to show some, all or no animations.
• Screen timeout	Touch to set screen timeout.

10.6 Location

Use the Location settings to set your preferences for using and sharing your location when your search for information and use location-aware applications, such as Google Maps.

10.6.1 My Location

Use wireless networks

Mark the check box to use information from Wi-Fi and mobile networks to determine your approximate location, for use in Google Maps, when you search, and so on. When you select this option, you're asked whether you consent to sharing your location anonymously with Google's location service.

Use GPS satellites

Check to use your phone's global positioning system (GPS) satellite receiver to pinpoint your location within an accuracy as close as several meters ("street level"). The process of accessing the GPS satellite and setting your phone's precise location for the first time will require up to 5 minutes. You will need to stand in a place with a clear view of the sky and avoid moving. After this, GPS will only need 20-40 seconds to identify your precise location.

GPS EPO assistance

Check to enable EPO (Extended Prediction Orbit) assistance. EPO is one of the off-line server based A-GPS technologies. It supports up to 30 days satellite orbit prediction, which can be used to greatly improve user experience by speeding up GPS Time To First Fix (TTFF).

EPO settings

 Auto download 	Mark the check box to permit applications to download data according to their own schedule.
• EPO file info	Check download time, start time and expiry time for satellite position data.

• About EPO Touch to learn more.

Touch **Download** at the bottom of the screen to download satellite position data manually.

A-GPS/A-GPS settings

Check to enable A-GPS (assisted GPS), which improves the startup performance, or time-to-first-fix (TTFF) of a GPS satellite-based positioning system.

- Disable after Select to disable A-GPS capability after reboot.
- Network request Select to allow network to request position.
- Profile selector Select a profile selector.
- Mobile network Check data connection status.

10.7 Security

Use the Security settings to define your usage preferences. You can also configure settings that help secure your phone and its data.

10.7.1 Screen unlock

Set up screen lock

- None Touch to disable screen unlock security.
- **Pattern** Touch to draw pattern to unlock screen.
- **PIN** Touch to enter a numeric PIN to unlock screen.
- Password Touch to enter a password to unlock screen.

10.7.2 SIM card lock

Set up SIM card lock

Opens a screen where you can configure the PIN required to use the phone, and where you can change the SIM PIN.

10.7.3 Passwords

Visible passwords

Mark the check box to show password as you type.

10.7.4 Device administration

Touch to add or remove device administrators.

10.7.5 Credential storage

Use secure credentials

Mark the check box to allow applications to access your phone's encrypted store of secure certificates and related passwords and other credentials. Credential storage is used to establish some kinds of VPN and Wi-Fi connections. If you have not set a password for the credential storage, this setting is dimmed.

Install from SD card

Touch to install encrypted certificates from the microSD card.

Set password

Touch to set or change a password for the credential storage (at least 8 characters).

Clear storage

Touch to clear credential storage of all contents and reset its password.

10.8 Applications

You use the Applications settings to view details about the applications installed on your phone, to manage their data and force them to stop, and to set whether you want to permit installation of applications that you obtain from web sites and email.

Unknown sources

Mark the check box to permit installation of applications that you obtain from web sites, email, or other locations other than Android Market.

To protect your phone and personal data, download applications only from trusted sources, such as Android Market.

Manage applications

Touch to manage and remove installed applications.

Running services

Touch to open a list of services—applications or parts of applications that provide services to other applications, or that run even when their main application isn't running. Examples include the Android onscreen keyboard and the small portion of Google Talk that always listens for incoming messages. Above each service, one or more gray bars show what processes the running service needs and how much memory they're using (how much memory you would recover if you stopped the service). Depending on the service, when you touch it in the list it either opens a dialog in which you can stop it or opens its Settings screen.

Storage use

Touch to view available memory and the memory used by applications on your phone.

Battery use

Touch to view the amount of power consumed by your phone. It also shows which applications consume the most battery power. For more information, refer to section 10.17 About phone.

Development

The Development screen contains settings that are useful for developing Android applications. For full information, including documentation of the Android applications and development tools, see the Android developer web site (http://developer.android.com).

- **USB debugging:** mark the check box to permit debugging tools on a computer to communicate with your phone via a USB connection.
- Stay awake: mark the check box to prevent the screen from dimming and locking when the phone is connected to a charger or to a USB device that provides power. Don't use this setting with a static image on the phone for long periods of time, or the screen may be marked with that image.
- Allow mock locations: mark the check box to permit a development tool on a computer to control where the phone believes it is located, rather than using the phone's own internal tools for this purpose.

10.9 Accounts & sync

Use the Accounts & Sync settings to add, remove, and manage your Google and other supported accounts. You also use these settings to control how and whether all applications send, receive, and synchronize data on their own schedules, and whether all applications can synchronize user data automatically.

Gmail, Google Calendar, and other applications may also have their own settings to control how they synchronize data; see the sections on those applications for details.

10.9.1 General sync settings

Background data

Mark the check box to permit applications to synchronize data in the background, whether or not you are actively working in them. Unmarking this setting can save battery power and lowers (but does not eliminate) data use.

Auto-sync

Mark the check box to permit applications to synchronize data on their own schedule. If you unmark this setting, you must touch an account in the list on this screen, touch **Sync now** to synchronize data for that account.

Synchronizing data automatically is disabled if **Background data** is unchecked. In that case, the **Auto-sync** checkbox is dimmed.

10.9.2 Manage accounts

The rest of this screen lists the Google Accounts and other accounts you've added to the phone. If you touch an account in this screen, its account screen opens.

This screen contains different options, depending on the kind of account. For Google Accounts, it lists the kinds of data you can synchronize to the phone, with checkboxes so you can turn synchronizing on and off for each kind. You can also touch **Sync now** to synchronize data. Press **Menu** key and touch **Remove account** to remove the account along with all its data (contacts, mail, settings, and so on).

10.10 Privacy

You use the Privacy settings to manage your personal information.

Back up my data

Mark the check box to back up your phone's settings and other application data to Google Servers, with your Google Account. If you replace your phone, the settings and data you've backed up are restored onto the new phone the first time you sign in with your Google Account. If you mark this option, a wide variety of settings and data are backed up, including your Wi-Fi passwords, bookmarks, a list of the applications you've installed, the words you've added to the dictionary used by the onscreen keyboard, and most of the settings that you configure with the Settings application. If you unmark this option, you stop backing up your settings, and any existing backups are deleted from Google Servers.

Automatic restore

Mark the check box to restore your backed up settings or other data when you reinstall an application.

Factory data reset

Erase all of your personal data from internal phone storage, including information about your Google Account, any other accounts, your system and application settings, and any downloaded applications. You can also mark the **Erase SD card** check box to erase all the data on your microSD card, such as music or photos. If you reset the phone in this way, you're prompted to re-enter the same kind of information as when you first started Android.

When you are unable to power on your phone, there is another way to perform a factory data reset by using hardware keys. Hold down **Volume down** key and press **Power** key at same time until the screen lights up and then press **Home** key.

10.11 SD card & phone storage

Use the microSD card & Phone Storage settings to monitor the total and available space on your phone and on your microSD card; to manage your microSD card; and if necessary, to reset the phone, erasing all of your personal information.

IO.II.I SD card

Total space/Available space

Lists the amount of space on any microSD card installed in your phone and the amount you can use to store photos, videos, music, and other files.

Unmount SD card

Unmounts the microSD card from your phone so that you can format the card or safely remove it when the phone is on. This setting is dimmed if there is no microSD card installed, if you have already unmounted it, or if you have mounted the microSD card on your computer.

Erase SD card

Permanently erases everything on a microSD card and prepares it for use with your phone. You must unmount a microSD card before you can format it.

10.11.2 Internal storage

Available space

Display the amount of internal phone storage used by the operating system, its components, applications (including those you downloaded), and their permanent and temporary data.



If a warning message comes up saying that phone memory is limited, you are required to free up space by deleting some unwanted applications, downloaded files etc.

10.12 Language & keyboard

Use the Language & keyboard settings to select the language for the text on your phone and for configuring the onscreen keyboard, including words that you've added to its dictionary.

10.12.1 Select language

Touch to select language and region you want.

10.12.2 User dictionary

Touch to open a list of the words you've added to the dictionary. Touch a word to edit or delete it. Press Menu key and touch Add to add a word.

10.12.3 Android keyboard

For phones with physical keyboards, unmark to disable the onscreen keyboard.

The Android keyboard settings apply to the onscreen keyboard that is included with your phone. The correction and capitalization features affect only the English version of the keyboard. Available options are as follows:

Vibrate on keypress

Mark the check box to have the phone vibrate briefly each time you touch a key on the onscreen keyboard.

Sound on keypress

Mark the check box to play a brief sound each time you touch a key on the onscreen keyboard.

Popup on keypress

Touching a key causes a larger image of itself to pop up when this check box is marked.

Touch to correct words

Marking this check box will underline any word that is touched in a text field, if the keyboard can suggest alternatives.

Auto-capitalization

Mark the check box to have the onscreen keyboard automatically capitalize the first letter of the first word after a period, the first word in a text field, and each word in name fields.

Show settings key

Touch to display or not the settings key.

Voice input

Touch to display or not the Mic button on keyboard.

• Input languages Touch to set input language.

• Quick fixes Correct commonly typed mistakes.

Show suggestions

Display suggested words while typing.

• Auto-complete Spacebar and punctuation automatically insert highlighted word.

10.12.4 Select input method Touch to open a dialog where you can select a default input method.

10.13 Voice input & output

10.13.1 Voice recognizer settings

Touch to set Google voice recognition items:

- Language Choose an input language
- SafeSearch Set Google Search safety range
- Block offensive Mark the check box to hide recognized offensive voice results

10.13.2 Text-to-speech settings ⁽¹⁾

You use the Text-to-Speech settings to configure the Android text-to-speech synthesizer, for applications like TalkBack that can take advantage of it.

If you don't have speech synthesizer data installed, only the Install voice data setting is available.

Listen to an example

Touch to play a brief sample of the speech synthesizer, using your current settings.

Install voice data

If your phone does not have speech synthesizer data installed, connect to Android Market and find yourself guided through the process of downloading and installing the data. This setting is not available if the data is already installed.

Always use my settings

Mark the check box to use the settings on this screen in place of speech synthesizer settings available in other applications.

Default engine

Touch to open a dialog where you can select which text-to-speech application you want to set as default.

Speech rate

Touch to open a dialog where you can select how quickly you want the synthesizer to speak.

 $[\]ensuremath{^{(l)}}$ $\ensuremath{$ Availability depending on your country and network operator.

Language

Touch to open a dialog where you can select the language of the text you want the synthesizer to read. This is particularly useful in combination with Always Use My Settings, to ensure that text is spoken correctly in a variety of applications.

Engines

Lists the engines installed on your phone.

10.14 Accessibility ⁽¹⁾

You use the Accessibility settings to configure any accessibility plug-ins you have installed on your phone.

Accessibility

Mark the check box to enable all installed accessibility plug-ins.

Power button ends call

Mark the check box to end a call by pressing **Power** key during the call.

Quick boot

Mark the check box to disable quick boot by pressing **Power** key.

Hearing aid

Mark the check box to turn on the hearing aid.

10.15 Date & time

Use Date & Time settings to customize your preferences for how date and time are displayed.

Automatic

Mark the check box to use network-provided values. Or unmark to set all values manually.

Set date

Touch to open a dialog where you can manually set the phone's date.

Select time zone

Touch to open a dialog where you can set the phone's time zone.

Set time

Opens a dialog where you can set the phone's time.

Use 24-hour format

Mark the check box to display the time using 24-hour clock format.

Select date format

Touch to open a dialog where you can select the format for displaying dates.

10.16 Schedule power on/off

You can use Schedule power on/off to set your phone to power on/off.

Mark the check box to activate the action.

10.17 About phone

Actually this contains information about a lot of things ranging from Legal information, Model number, Firmware version, Baseband version, Kernel version, Build number to those listed below:

System updates

System updates, or Firmware Upgrade Manager, gives you the option of downloading a firmware upgrade over the air directly from your mobile phone service provider. It ensures that you have the latest software improvements to enhance the features and performance on your phone.

- Check for update Manually check for new firmware.
- Settings Below items are able to set: Wi-Fi only, Daily auto-check, Auto-check intervals, Upgrade status reminder.
- Help

- Touch to learn more.
- The functions below may incur additional network charges from your network operator. Extra fees may also be charged in roaming areas. To ensure a more stable, faster speed, you are strongly recommended to connect by Wi-Fi when you download firmware.

Status

This contains the status of the Battery status, Battery level, SIM status, IMEI information, Wi-Fi MAC address, Bluetooth address, Up time.

Battery use

Touch to open a list of the applications and operating system components you have used since you last connected the phone to a power source, sorted by the amount of power they have used. Touch an application in the list to view details about its power use and, if available, touch a button to open a settings or information screen for that component or application.

Legal information

Touch to view legal information.

Others

Other information about the phone, such as model number, firmware version, build number, etc.

Making the most of your phone

You can download software upgrade for free from the website: www. alcatelonetouch.com.

II.I Android Manager

The Android Manager includes:

Contacts

It allows you to back up contact entries so that you don't have to worry about losing, breaking, switching phone or changing service providers.

Messages

It frees you from painstakingly inputting text on the keypads. All of your messages are easily accessible and well-organized.

• Photos

It allows you to easily import photos from PC or the handset and organize them in different albums for better management.

Videos

It allows you to insert video files from PC for playback and then upload to handset folder.

Music

It allows you to quickly search your favourites in PC, manage the ultimate Library, and enjoy the easiest digital jukebox in your own mobile way.

Application

It allows you to import downloaded mobile applications and have them installed into your handset upon synchronization.

• File

It allows you to organize Handset files with just a few clicks and files on the Handset can be at where you want them to be.

• Sync

It allows you to synchronize the Contacts and Calendar in Outlook/ Outlook Express and handset.

Supported Operating Systems

Windows XP/Vista/Windows 7.

II.2 Upgrade

You can use ONE TOUCH Upgrade tool or FOTA Upgrade tool to update your phone's software.

11.2.1 ONE TOUCH Upgrade

Using ONE TOUCH Upgrade tool you can update your phone's software from your PC.

Download ONE TOUCH Upgrade from ALCATEL ONE TOUCH website (www.alcatelonetouch.com) and install it on your PC. Launch the tool and update your phone by following the step by step instructions (refer to the User Guide provided together with the tool).

Your phone's software will now have the latest software.

<u>ģ</u>-

All personal information will be permanently lost following the update process. We recommend you backup your personal data using Android Manager before upgrading.

Supported Operating Systems

Windows XP/Vista/Windows 7.

11.2.2 FOTA Upgrade

Using FOTA Upgrade tool you can update your phone's software:

- Press Menu key from Home screen
- Touch Settings\About phone\System updates\Check for Updates, the phone will search for the latest software.

If you want to update the system, please touch the button **Download**. After it's done please touch **Install** to complete the upgrade. Now your phone's software will have the latest version.



During FOTA downloading or updating, to avoid errors in locating the correct update packages, do not change your default storage location.

2 Telephone warranty

Your phone is warranted against any defect or malfunctioning which may occur in conditions of normal use during the warranty period of twelve (12) months $^{(\mathrm{l})}$ from the date of purchase as shown on your original invoice.

Batteries $^{(2)}$ and accessories sold with your phone are also warranted against any defect which may occur during the first six (6) months $^{(1)}$ from the date of purchase as shown on your original invoice.

In case of any defect of your phone which prevents you from normal use thereof, you must immediately inform your vendor and present your phone with your proof of purchase.

If the defect is confirmed, your phone or part thereof will be either replaced or repaired, as appropriate. Repaired phone and accessories are entitled to a one (1) month warranty for the same defect. Repair or replacement may be carried out using reconditioned components offering equivalent functionality.

This warranty covers the cost of parts and labor but excludes any other costs.

- ⁽¹⁾ The warranty period may vary depending on your country.
- ⁽²⁾ The life of a rechargeable mobile phone battery in terms of conversation time standby time, and total service life, will depend on the conditions of use and network configuration. Batteries being considered expendable supplies, the specifications state that you should obtain optimal performance for your phone during the first six months after purchase and for approximately 200 more recharges.

This warranty shall not apply to defects to your phone and/or accessory due to (without any limitation):

- Non-compliance with the instructions for use or installation, or with technical and safety standards applicable in the geographical area where your phone is used,
- 2) Connection to any equipment not supplied or not recommended by TCT Mobile Limited,
- Modification or repair performed by individuals not authorised by TCT Mobile Limited or its affiliates or your vendor,
- 4) Inclement weather, lightning, fire, humidity, infiltration of liquids or foods, chemical products, download of files, crash, high voltage, corrosion, oxidation...

Your phone will not be repaired in cases where labels or serial numbers (IMEI) have been removed or altered.

There are no express warranties, whether written, oral or implied, other than this printed limited warranty or the mandatory warranty provided by your country or jurisdiction.

In no event shall TCT Mobile Limited or any of its affiliates be liable for indirect, incidental or consequential damages of any nature whatsoever, including but not limited commercial or financial loss or damage, loss of data or loss of image to the full extent those damages can be disclaimed by law.

Some countries/states do not allow the exclusion or limitation of indirect, incidental or consequential damages, or limitation of the duration of implied warranties, so the preceding limitations or exclusions may not apply to you.

3 Accessories ⁽¹⁾.....

The latest generation of ALCATEL ONE TOUCH GSM mobile phones offers a built-in handsfree feature that allows you to use the telephone from a distance, placed on a table for example. For those who prefer to keep their conversations confidential, an earpiece is also available known as the headset.



^(I) Pictures for reference only.

4 Troubleshooting.....

Before contacting the service centre, you are advised to follow the instructions below:

- You are advised to fully charge () the battery for optimal operation.
- Avoid storing large amounts of data in your phone as this may affect its performance.
- Use Factory data reset and the FOTA/ONE TOUCH Upgrade tool to perform phone formatting or software upgrading, (to reset User Data format, hold down Volume up key while simultaneously pressing the Power key).
 ALL User phone data: contacts, photos, messages and files, downloaded applications like APK games will be lost permanently. It is strongly advised to fully backup the phone data and profile via Android Manager before doing formatting and upgrading.

and carry out the following checks:

My phone is frozen or cannot switch on

- Check the battery contacts, remove and reinstall your battery, then turn your phone on
- · Check the battery power level, charge for at least 20 minutes
- If it still does not work, please use Factory data reset to reset the phone or FOTA/ONE TOUCH Upgrade to upgrade software

My phone has not responded for several minutes

- Restart your phone by pressing and holding the **Power** key
- · Remove the battery and re-insert it, then restart the phone
- If it still does not work, please use Factory data reset to reset the phone or FOTA/ONE TOUCH Upgrade to upgrade software

My phone turns off by itself

- Check that your keypad is locked when you are not using your phone, and make sure **Power** key is not mis-contacted due to unlocking keypad
- · Check the battery charge level
- If it still does not work, please use Factory data reset to reset the phone or FOTA/ONE TOUCH Upgrade to upgrade software

My phone cannot charge properly

- \bullet Make sure you are using an ALCATEL ONE TOUCH battery and the charger from the box
- Make sure your battery is inserted properly and clean the battery contact if it's dirty. It must be inserted before plugging in the charger
- Make sure that your battery is not completely discharged; if the battery power is empty for a long time, it may take around 20 minutes to display the battery charger indicator on the screen
- Make sure charging is carried out under normal conditions (0°C to +40°C)
- · When abroad, check that the voltage input is compatible

My phone cannot connect to a network or "No service" is displayed

- Try connecting in another location
- · Verify the network coverage with your operator
- · Check with your operator that your SIM card is valid
- Try selecting the available network(s) manually (see Page 67)
- Try connecting at a later time if the network is overloaded

My phone cannot connect to the Internet

- Check that the IMEI number (press #06#) is the same as the one printed on your warranty card or box
- Make sure that the internet access service of your SIM card is available
- Check your phone's Internet connecting settings
- Make sure you are in a place with network coverage
- Try connecting at a later time or another location

Invalid SIM card

- Make sure the SIM card has been correctly inserted (see Page 16)
- Make sure the chip on your SIM card is not damaged or scratched
- Make sure the service of your SIM card is available

Unable to make outgoing calls

- Make sure you have dialed a valid number and touch 📞
- · For international calls, check the country and area codes
- Make sure your phone is connected to a network, and the network is not overloaded or unavailable
- Check your subscription status with your operator (credit, SIM card valid, etc.)
- Make sure you have not barred outgoing calls
- Make sure that your phone is not in flight mode

Unable to receive incoming calls

- Make sure your phone is switched on and connected to a network (check for overloaded or unavailable network)
- Check your subscription status with your operator (credit, SIM card valid, etc.)
- · Make sure you have not forwarded incoming calls
- Make sure that you have not barred certain calls
- Make sure that your phone is not in flight mode

The caller's name/number does not appear when a call is received

- · Check that you have subscribed to this service with your operator
- · Your caller has concealed his/her name or number

I cannot find my contacts

- Make sure your SIM card is not broken
- Make sure your SIM card is inserted properly
- Import all contacts stored in SIM card to phone

The sound quality of the calls is poor

- You can adjust the volume during a call by pressing the Volume key
- Check the network strength _____
- Make sure that the receiver, connector or speaker on your phone is clean

I am unable to use the features described in the manual

- Check with your operator to make sure that your subscription includes this service
- Make sure this feature does not require an ALCATEL ONE TOUCH accessory

When I select a number from my contacts, the number cannot be dialed

- Make sure that you have correctly recorded the number in your file
- Make sure that you have selected the country prefix when calling a foreign country

I am unable to add a contact in my contacts

• Make sure that your SIM card contacts are not full; delete some files or save the files in the phone contacts (i.e. your professional or personal directories)

My callers are unable to leave messages on my voice mail

Contact your network operator to check service availability

I cannot access my voice mail

- Make sure your operator's voice mail number is correctly entered in "My numbers"
- Try later if the network is busy

I am unable to send and receive MMS

- · Check your phone memory availability as it might be full
- Contact your network operator to check service availability and check MMS parameters (see Page 50)
- Verify the server centre number or your MMS profile with your operator
- The server centre may be swamped, try again later

SIM card PIN locked

Contact your network operator to obtain the PUK code (Personal Unblocking Key)

I am unable to connect my phone to my computer

- Install ALCATEL ONE TOUCH Android Manager first of all
- Check that your USB driver is installed properly
- Open the Notification panel to check if the Android Manager Agent has activated
- Check that you have ticked the checkbox of USB debugging in Settings\ Applications\Development\USB debugging
- Check that your computer meets the requirements for ALCATEL ONE TOUCH Android Manager Installation
- Make sure that you're using the right cable from the box

I am unable to download new files

- Make sure there is sufficient phone memory for your download
- Select the micro-SD card as the location to store downloaded files
- · Check your subscription status with your operator

The phone cannot be detected by others via Bluetooth

- Make sure that Bluetooth is turned on and your phone is visible to other users (see Page 80)
- Make sure that the two phones are within Bluetooth's detection range

How to make your battery last longer

- Make sure you follow the complete charge time (minimum 3 hours)
- After a partial charge, the battery level indicator may not be exact. Wait for at least 20 minutes after removing the charger to obtain an exact indication
- Switch on the backlight upon request
- Extend the email auto-check interval for as long as possible
- Update news and weather information on manual demand, or increase their auto-check interval
- Exit background-running applications if they are not being used for a long time
- Deactivate Bluetooth, Wi-Fi, or GPS when not in use

The phone becomes warm after prolonged calls, game playing, internet surfing or running other complex applications

• This heating is a normal consequence of the CPU handling excessive data. Ending above actions will make your phone return to normal temperature

5 Specifications

Processor	Platform MTK6575M
Platform	Android [™] 2.3
Memory	ROM: 512 MB
	RAM: 256 MB
Dimensions (LxWxT)	115 × 62.3 × 12.2 mm
Weight	Around 118 grams with battery
Display	3.5-inch TFT-LCD touchscreen with 320×480 HVGA resolution
	UMTS:
	Dual-band 900/2100 MHz (EU); tri-band 850/1900/2100 MHz (US)
Network	GSM/GPRS/EDGE:
	Quad-band 850/900/1800/1900 MHz
	(Band frequency and data speed are operator dependent.)
GPS	Assisted GPS/Internal GPS antenna
	Bluetooth [®] 4.0 A2DP
Connectivity	• Wi-Fi [®] : IEEE 802.11 b/g/n
	• 3.5 mm audio jack
	• micro-USB

Camera	2.0 megapixel color camera
Audio supported formats	AAC, AAC+, AAC Enhanced, WB AMR, MP3, Midi, eAAC
Video supported formats	MPEG-4 (playback only), H.263, H.264 (playback only)
Battery	 Rechargeable Lithium-ion battery Capacity: 1300 mAh
Expansion Slot	microSD [™] memory card (Availability of microSD card depends on market)
Special Features	G-sensorLight sensorProximity sensor

Note Specifications are subject to change without prior notice.

ALCATEL is a trademark of Alcatel-Lucent and is used under license by TCT Mobile Limited.	
© Copyright 2013 TCT Mobile Limited All rights reserved	
TCT Mobile Limited reserves the right to alter material or technical specification without prior notice.	

All "Signature" ringtones embedded in this phone have been composed, arranged and mixed by NUTROPIC (Amar Kabouche).

English - CJB26NAALAAA